



Packing List:

FX-301B



FX-301B-11 with 50mm x50mm Solder Pot (A1539), British Power Cord + Instruction Manual



J Shaped Waste Collector (B2919)



Spatula (B2932)



Hexagon wrench (B1417)



Specifications:

FX-301B


Power consumption	260W (230V)
Dimensions	143(W)×100(H)×220(D)mm
Weight	1.7kg
Weight	0.75kg

^{*} Weight (w/o solder, cord)

Pot


Temperature range	50×50 square : 200 to 450°C 75×75 square : 200 to 380°C
Dimensions of solder pot	50×50 square durable type : $50(W)\times42.2(H)\times50(D)mm$ 75×75 square durable type : $75(W)\times51.2(H)\times75(D)mm$
Molten solder capacity	50×50 square : 0.85kg 75×75 square : 1.2kg

Easy Pot Replacement:




Ensure the pot is cold and loosen the screws

Replace the pot and tighten the screws



A1539 (Included) A1517



Available to purchase separately

Recommended Extras:

Available to purchase separately



A1517 50mm Solder Pot



A1518 75mm Solder Pot



A1540 Durable 75mm Solder Pot



FG100B Thermometer + A1310 Solder Pot Probe

