Product data sheet Characteristics

GV7AS107

Voltage release, TeSys GV5 GV6 GV7, MX shunt trip, 110-130V AC 50/60Hz



Range	TeSys	
Product or component type	Shunt trip	
Device short name	GV7AS	- <u> </u>
Device application	Control	
Range compatibility	TeSys GV5 TeSys GV6 TeSys GV7	o de la companya de l

Complementary

Complementary		
[Uc] control circuit voltage	110130 V AC 50/60 Hz	
Control circuit voltage limits	0.71.1 Un	
[Ui] rated insulation voltage	690 V AC conforming to IEC 60947-1 600 V AC conforming to UL 508 600 V AC conforming to CSA C22.2 No 14	rin Adalah
Threshold tripping voltage	0.20.75 Ue	
Inrush power in VA	10 VA AC	
Hold-in power consumption in VA	5 VA AC	
Operating time	< 50 ms conforming to IEC 60947-1	
On-load factor	100 %	
Connections - terminals	Screw clamp terminals 1 cable(s) 1 mm²flexible with cable end Screw clamp terminals 1 cable(s) 1.5 mm²flexible without cable end Screw clamp terminals 1 cable(s) 1.5 mm²solid	
Tightening torque	1.2 N.m on screw clamp terminals	**************************************
Net weight	0.105 kg	-2
Quantity per set	Set of 10	- 0 - 0 - 0

Offer Sustainability

		U
REACh free of SVHC	Yes	
EU RoHS Directive	Compliant EU RoHS Declaration	
Toxic heavy metal free	Yes	يَ -
Mercury free	Yes	Ė.
RoHS exemption information	Yes	

China RoHS Regulation	China RoHS declaration Pro-active China RoHS declaration (out of China RoHS legal scope)
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins
Contractual warranty	
Warranty	18 months