





## Features:

- A low noise high gain pre-amplifier for use with magnetic cartridges, or dynamic/condenser microphones.
- Used on any amplifier with "Phono" input.
- IC technology, for high gain with low noise.
- CE certified.
- Suitable for a stereo microphone, or two mono microphones.
- Strong stylish steel case.
- Power supply included.

## **Technical Specifications:**

Input impedance: 50KInput level: 0.5mGain: 50dESignal/noise ratio: >48dPhono mode frequency response (mic.): +1dEEqualisation (phono): RIAAOutput level: 150mLoad impedance: >10kOverload margin: 23dE

- : 50K ohms at 1kHz.
- : 0.5mV mic. mode/3mV phono mode.
- : 50dB mic. mode/34dB phono mode.
- : >48dB mic. mode/>55dB.
- : +1dB to -3dB, 70Hz to 20kHz.
- : RIAA +1dB to -3dB, 30Hz to 20kHz.
- : 150mV RMS.
- : >10K ohms.
- : 23dB, crosstalk 55dB, supply voltage 12 to 15V dc, 100mA, 1.3mm DC socket.

## **Part Number Table**

Description	Part Number
Pre-Amplifier	AV01280

Disclaimer This data sheet and its contents (the "Information") belong to the Premier Farnell Group (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheets here should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. SPC pro-SIGNAL is the registered trademark of the Group. © Premier Farnell plc 2009.

http://www.farnell.com http://www.newark.com http://www.cpc.co.uk

