# Data sheet | Item number: 207-1333 Gelbox; for cables; Branch; with gel; 221, 2x73 Series; max. 4 mm<sup>2</sup> connectors; without splicing connectors; Size 3; gray



www.wago.com/207-1333



Subject to changes. Please also observe the further product documentation!

WAGO Private Limited NH No. 8, Block No. 94 Vadsala, Block No. 1187 Varnama, Village Varnama / Vadsala Ta. & Distt. Vadodara, Vadodara, Gujarat-391243 Phone: +91-265-6812100 | Email: info.india@wago.com Do you have any questions about our products? We are always happy to take your call at +49 (571) 887-44222.



#### Item description

Note on Packaging Unit (PU) and Subpackaging Unit (SPU): If you order a full PU, you will receive our eco-friendly, sustainable cardboard blisters packed in a shelf-ready box. If you order a quantity smaller than a full PU, you will receive the eco-friendly, sustainable cardboard blisters without a shelf-ready box.

Please note the system description for the splicing connectors that can be used.

The Benefits for You:

- Easy, fast and safe to use
- Can be used immediately and accessed again later
- Silicon-free
- Label-free
- Suitable for indefinite storage
- The complete system consisting of Gelboxes and WAGO connectors has been VDE-tested and IPX8-certified.

### Data Connection data

#### **Connection 1**

| Actuation type | Locking system |
|----------------|----------------|
|                |                |

### Physical data

| Width  | 33.6 mm / 1.323 inch |
|--------|----------------------|
| Height | 17.8 mm / 0.701 inch |
| Depth  | 52.7 mm / 2.075 inch |

#### Mechanical data

| Mounting type    | Flying leads |
|------------------|--------------|
| Protection class | IPX8         |

#### Material data

| Note on material data | Information on material data can be found here |  |
|-----------------------|--|--|
| Color                 | gray   |  |
| Housing material      | Polypropylene                                  |  |
| Weight                | 21 g   |  |

Subject to changes. Please also observe the further product documentation!

| WAGO Private Limited                                | Do you have any questions about our products?                 |
|---|---|
| NH No. 8, Block No. 94 Vadsala,                     | We are always happy to take your call at +49 (571) 887-44222. |
| Block No. 1187 Varnama, Village Varnama / Vadsala   |   |
| Ta. & Distt. Vadodara, Vadodara, Gujarat-391243     |   |
| Phone: +91-265-6812100   Email: info.india@wago.com |   |

www.wago.com/207-1333



### **Environmental requirements**

| Surrounding air temperature (operation) | -55 85 °C |
|---|-----------|
| Surrounding air temperature (storage)   | 0 40 °C   |

### **Commercial data**

| PU (SPU)              | 36 (3) Stück  |
|-----------------------|---------------|
| Packaging type        | BOX           |
| Country of origin     | IT            |
| GTIN                  | 4055143997805 |
| Customs tariff number | 85389099990   |

### Approvals / Certificates

### **Country specific Approvals**

|      |                                       |                          | Certificate |
|------|---------------------------------------|--------------------------|-------------|
| Logo | Approval                              | Additional Approval Text | name        |
|      | VDE                                   | EN 60998                 | 400051938   |
| VDE  | VDE Prüf- und Zertifizierungsinstitut |                          |             |

## Downloads Documentation

**Bid Text** 

| 207-1333                                | docx          | Download |
|---|---------------|----------|
| doc - Datei                             | 20.9 kB       |          |
| 207-1333                                | xml           | Download |
| X81 - Datei                             | 3.7 kB        |          |
| System Description                      |               |          |
| System Description 207 Series Gel boxes | pdf<br>1.2 MB | Download |
| Additional Information                  |               |          |
| Technical Section                       | pdf           | Download |
| Technical explanations                  | 2.2 MB        |          |

Subject to changes. Please also observe the further product documentation!

| WAGO Private Limited                                | Do you have any questions about our products?                 |
|---|---|
| NH No. 8, Block No. 94 Vadsala,                     | We are always happy to take your call at +49 (571) 887-44222. |
| Block No. 1187 Varnama, Village Varnama / Vadsala   |   |
| Ta. & Distt. Vadodara, Vadodara, Gujarat-391243     |   |
| Phone: +91-265-6812100   Email: info.india@wago.com |   |



#### CAD/CAE-Data

| CAD data   |     |          |
|--|-----|----------|
| 2D/3D Models 207-1333  | URL | Download |
| CAE data   |     |          |
| ZUKEN Portal 207-1333  | URL | Download |
|  |     |          |
| Environmental Product Compliance   |     |          |
| Compliance Search  |     |          |
| Environmental Product Compliance 207-1333  | URL | Download |
| Gelbox; for cables; Branch; with gel; 221, 2x73 Series; max. 4 mm <sup>2</sup> connectors; |     |          |

without splicing connectors; Size 3; gray


### Installation Notes

#### Installation

Gelbox öffnen.



Place the wired connector in the Gelbox.




Place the wired connector in the Gelbox.

Subject to changes. Please also observe the further product documentation!

WAGO Private Limited NH No. 8, Block No. 94 Vadsala, Block No. 1187 Varnama, Village Varnama / Vadsala Ta. & Distt. Vadodara, Vadodara, Gujarat-391243 Phone: +91-265-6812100 | Email: info.india@wago.com Do you have any questions about our products? We are always happy to take your call at +49 (571) 887-44222.





Close the Gelbox.



Close latch securely.



Re-accessible:

- Open the Gelbox.
- Remove the gel.
- Rewire with new components.

Tear off the cover from the perforation.



Lift the flap and pull the cover perforation forward.



Press in the perforation on the sides.



As a counter display: Bend the rear flap at the fold, straighten it and fix it in the cardboard cut-out If the flap is not required, tear off from the perforation.

Subject to changes. Please also observe the further product documentation!

WAGO Private Limited NH No. 8, Block No. 94 Vadsala, Block No. 1187 Varnama, Village Varnama / Vadsala Ta. & Distt. Vadodara, Vadodara, Gujarat-391243 Phone: +91-265-6812100 | Email: info.india@wago.com Do you have any questions about our products? We are always happy to take your call at +49 (571) 887-44222.