# SHC68-C68-D4 Specifications





# Contents

# Specifications

This document lists the specifications for the SHC68-C68-D4. Specifications in this document are nominal unless otherwise noted. Specifications are subject to change without notice. Refer to <u>ni.com/manuals</u> the most recent specifications.

**Caution** Do not exceed the operating specifications for the device connected to the SHC68-C68-D4. Refer to the documentation for your highspeed digital device for the warranted, maximum operating temperature, additional environmental requirements, and pinouts.

The SHC68-C68-D4 is available with the following options and lengths:

- 0.55 m (781013-01)
- 1 m (196275-01)
- 1 m low leakage[1] (152870-01)
- 2 m (781293-01)

Visit <u>ni.com/info</u> and enter the Info Code D4COMPATIBILITY for a list of devices and accessories that are compatible with the SHC68-C68-D4.

## **Electrical Specifications**

Maximum voltage			±30 VDC	
Specification	0.55 m	1 m and 1 m Low-Leakage <sup>[1]</sup>		2 m
Characteristic impedance	50 Ω ±10%	50 Ω ±10%		50 Ω ±10%
Resistance	0.3 Ω	0.5 Ω		1Ω
Capacitance	60 pF	100 pF		200 pF
Propagation delay	2.7 ns	4.9 ns		9.6 ns
Channel-to-channel skew	50 ps	50 ps		75 ps

#### **Physical Characteristics**

175 g (6.2 oz)		
255 g (9.0 oz)		
435 g (15.3 oz)		
0.032 mm <sup>2</sup> (32 AWG)		
7/0.08 mm (7/40)		
68-pin male VHDCI connector (x2)		
40 single-ended channels		

### Safety

This product is designed to meet the requirements of the following electrical equipment safety standards for measurement, control, and laboratory use:

- IEC 61010-1, EN 61010-1
- UL 61010-1, CSA 61010-1

#### Worldwide Support and Services

Visit <u>ni.com/support</u> to find support resources including documentation, downloads, and troubleshooting and application development self-help such as tutorials and examples.

Visit <u>ni.com/services</u> to learn about NI service offerings such as calibration options, repair, and replacement.

Visit <u>ni.com/register</u> to register your NI product. Product registration facilitates technical support and ensures that you receive important information updates from NI.

NI corporate headquarters is located at 11500 N Mopac Expwy, Austin, TX, 78759-3504, USA.

<sup>1</sup> The PCB surfaces of low-leakage cables are cleaned of contaminants during manufacturing, reducing induced current leakage.