Panel Meter Moving Coil Meter









Specifications:

Movement : Moving coil type

 Measuring Range
 : 90°

 Pointer
 : 0.4m/m

 Pointer Colour
 : Red/Black

 Pointer Position
 : Left zero hand

 Scale
 : Aluminium

 Coil Resistance
 :1500Ω ±10%

 Current Sensitivity
 : DC 100uA ±2.5%


Friction Tolerance : ±0.4m/m


Balance : Within the pointer width ±0.4m/m vertically and horizontally


Over Current : Within 5 items of rate current
Operation Temperature : Between -20°C and +60°C
Zero Position Difference : Within width of pointer

+ Terminal : Right side when seen from front

Diagram







Specification Table

Туре	Full Scale Deflection	Case Dimension	Part Number
Ammeters	100μΑ	45 × 45	SD-38/0-100UA
	1mA		SD38/0-1MA
	20mA		SD38/0-20MA
	500mA		SD38/0-500MA
	1A		SD38/0-1A
	3A		SD38/0-3A
	5A		SD38/0-5A
Voltmeters	15V		SD38/0-15V
	30V		SD38/0-30V

Dimensions: Millimetres


Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro



Panel Meter Moving Coil Meter




Specification Table



Туре	Full Scale Deflection	Case Dimension	Part Number
Ammeters	100µA	60 × 60	SD60/0-100UA
	1mA		SD60/0-1MA
	20mA		SD60/0-20MA
	1A		SD60/0-1A
	5A		SD60/0-5A
	10A		SD60/0-10A
	15A		SD60/0-15A
	30A		SD60/0-30A
	50A		SD60/0-50A
Voltmeters	15V		SD60/0-15V
	30V		SD60/0-30V
	300V		SD60/0-300V

Dimensions: Millimetres

Specification Table



Type	Full Scale Deflection	Case Dimension	Part Number
Ammeters	100μΑ	81 × 81	SD80/0-100UA
	1mA		SD80/0-1MA
	1A		SD80/0-1A
	5A		SD80/0-5A
	10A		SD80/0-10A
	30A		SD80/0-30A
	50A		SD80/0-50A
Voltmeters	15V		SD80/0-15V
	30V		SD80/0-30V
	300V		SD80/0-300V

Dimensions : Millimetres

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro

