


Product Search Data Sheet

CSTLS32M0X51-A0

In Production Recommended RoHS REACH

Appearance & Shape



Note: This datasheet may be out of date. Please download the latest datasheet of CSTLS32M0X51-A0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=CSTLS32M0X51-A0



MURATA's ceramic resonator, CERALOCK(R) with built-in load capacitors, has been widely applied as the most suitable component for clock oscillators in a broad range of microprocessors. The CSTLS series can be used in the design of oscillation circuits not requiring external load capacitors, enabling both high-density mounting and cost reduction.

Features

1. Oscillation circuits do not require external load capacitors. There is some variation in built-in capacitance values applicable to various IC.

2. Stable over a wide temperature range.

3. Compact, lightweight and exhibit superior shock resistance performance.

4. Enable the design of oscillator circuits requiring no adjustment.

5. Cost-effective and reliable availability.



Applications

Other Usage

Consumer/Industrial

Packaging Information

Packaging		Standard
		Packing
		Quantity
A0	Ammo Pack	2000

1 of 2

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





CSTLS32M0X51-A0

Note: This datasheet may be out of date. Please download the latest datasheet of CSTLS32M0X51-A0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=CSTLS32M0X51-A0

Specifications

Product Type	Ceramic Resonator (CERALOCK)
Series	CSTLS_X
Frequency	32.000MHz
Frequency Tolerance	+/-0.50% max.
Operating Temperature Range	-20°C~80°C
Frequency Shift by Temperature	+/-0.20% max.
Frequency Aging	+/-0.20% max.
Resonant Impedance (R1)	50ohm max.
Built-in Load Capacitance (CL1/CL2)	5pF
Shape	Lead
Wash	Not available
L x W (size)	6.5x7.0mm
Mass	179mg

2 of 2

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

