

PRODUCT-DETAILS

F202 A-25/0.03 110V F202 A-25/0.03 110V Residual Current Circuit Breaker 2P A type 30 mA



General Information		
Extended Product Type	F202 A-25/0.03 110V	
Product ID	2CSF202199R1250	
EAN	8012542343332	
Catalog Description	F202 A-25/0.03 110V Residual Current Circuit Breaker 2P A type 30 mA	
Long Description	The RCCBs F200 series assures protection against the effects of sinusoidal alternating and direct pulsating earth fault currents, protection, against indirects contacts and additional protection against direct (with sensitivity = 30 mA) contacts. Applications: residential commercial, industrial. This particular serias has the minimum operating voltage of test buttom 0f 110V and it is suitable for application at 230V	
Circular Value Circular Design Principles	Design for Closing Resource Loops - Standard EN45555 - 52,5 %	
Recyclability Rate		
Sustainable Material Content	0 %	
End of Life Instructions	9AKK108468A4361	
Foo Trongneroney		
Eco Transparency		
Environmental Product Declaration - EPD	9AKK108467A3700	

F202 A-25/0.03 110V 2

Technical	
Standards	IEC 61008 UL 1053
Type of Residual Current	A type
Rated Voltage (U _r)	230 V
Rated Operational Voltage	230 V
Rated Insulation Voltage (U _i)	500 V
Test Voltage (Ut)	110 V
Rated Impulse Withstand Voltage (U _{imp})	4 kV
Input Voltage Type	AC
Rated Current (I _n)	25 A
Rated Residual Current	30 mA
Rated Conditional Short- Circuit Current (I _{nc})	10 kA
Rated Service Short- Circuit Breaking Capacity (I _{cs})	1 kA
Leakage Current Type	A
Rated Frequency (f)	50 60 Hz
Power Loss	at Rated Operating Conditions per Pole 1.0 W
Power Supply Connection	Arbitrary
Electrical Endurance	10000 cycle
Number of Poles	2
Operating Characteristic	Instantaneous
Mounting Type	DIN-Rail
Options Provided	None, Suitable for 110V applications
Accessories Available	Yes
Connecting Capacity	Busbar 10 mm² Rigid 25 25 mm² Flexible 25 25 mm²
Rated Cross-Section	4 - Multi-Wired 025 mm² 1 - Solid-Core 2525 mm²
Environmental	
Ambient Temperature	-2555 °C
Ambient Air Temperature	Operation -2555 °C
Degree of Protection	IP2X
Pollution Degree	2
Resistance to Vibrations acc. to IEC 60068-2-6	0.1 mm or 1 g - 20 cycles at 51505 Hz
Resistance to Shock acc. to IEC 60068-2-27	25g 2 shocks 13 ms
RoHS Status	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019
RoHS Information	9AKK106713A5602
REACH Declaration	9AKK108467A9482
Environmental Information	Refer to RoHS
SCIP	18f132b0-8f03-4611-9c59-dba03cc369bf Italy (IT)
Conflict Minerals Reporting Template (CMRT)	9AKK108468A3363

F202 A-25/0.03 110V

Technical UL/CSA			
Maximum Operating Voltage UL/CSA		277 V AC	
Short-Circuit Current Rating (SCCR)		30 mA	
Dimensions			
Width in Number of Modular Spacings		2	
Product Net Width		0.035 m	
Product Net Height		0.085 m	
Product Net Depth / .ength		0.069 m	
Product Net Weight		0.200 kg	
Built-In Depth (t ₂)		69 mm	
0.1			
Ordering Minimum Order Quantity		1 piece	
Package Level 1 Units		box 1 piece	
Package Level 1 Gross		0.235 kg	
Weight Customs Tariff Number		85363030	
E-Number (Finland)		3211068	
Country of Origin		Italy (IT)	
Declaration of Conformity - CE		9AKK106713A5602	
Popular Downloads			
Data Sheet, Technical Information		9AKK107991A8329	
Instructions and Manuals		9AKK107991A6127	
EPLAN Macro		9AKK106930A1238	
Classifications			
ETIM 8	EC000003 - Residual current circuit breaker (RCCB)		
ETIM 9	EC000003 - Residual current circuit breaker (RCCB)		
EPLAN Catalog Tree	Electrical engineering / Protection devices / Ground fault current circuit breaker		
EPLAN Function Definition	Ground fault current circuit-breaker / Ground fault current circuit breakers, 4 connection points / Ground fault current circuit breaker, two-pole 1/2 2/1 3/4 4/3		
WEEE Category	5. Small Equipment (No I	External Dimension More Than 50 cm)	
WEEE B2C / B2B		Business To Consumer	
CN8		85363030	
UNSPSC		39121601	
eClass		V11.0 : 27142201	
IDEA Granular Category		esidual current circuit breaker (RCCB)	
© 2023 ABB. All rights reserved.	2023/08/08	Subject to change v	

Code (IGCC)

Object Classification Code

Accessories				
ldentifier	Description	Туре	Quantity	Unit Of Measure
2CDS200912R0001	S2C-H6R Auxiliary Contact	S2C-H6R	2	piece
2CDS200922R0001	S2C-S/H6R Signal / Auxiliary Contact	S2C-S/H6R	2	piece
2CDS200946R0001	S2C-H6-11R Auxiliary Contact	S2C-H6-11R	1	piece
2CDS200946R0003	S2C-H6-02R Auxiliary Contact	S2C-H6-02R	1	piece
2CDS200946R0002	S2C-H6-20R Auxiliary Contact	S2C-H6-20R	1	piece
2CSS200933R0011	F2C-A1 Shunt trip	F2C-A1	1	piece
2CSS200933R0012	F2C-A2 Shunt trip	F2C-A2	1	piece
2CSS200911R0005	S2C-UA 230 AC Undervoltage release	S2C-UA 230 AC	1	piece
2CSS200911R0007	S2C-UA 24 DC Undervoltage release \$	1	piece	
2CSS200911R0002	S2C-UA 24 AC Undervoltage release S	1	piece	
2CSS200911R0008	S2C-UA 48 DC Undervoltage release \$	S2C-UA 48 DC	1	piece
2CSS200911R0004	S2C-UA 110 AC Undervoltage release	S2C-UA 110 AC	1	piece
2CSS200911R0006	S2C-UA 400 AC Undervoltage release	S2C-UA 400 AC	1	piece
2CSS200911R0001	S2C-UA 12 DC Undervoltage release S	S2C-UA 12 DC Undervoltage release S2C-UA 12 DC		
2CSS200911R0010	S2C-UA 230 DC Undervoltage release	S2C-UA 230 DC	1	piece
2CSS200911R0009	S2C-UA 110 DC Undervoltage release	S2C-UA 110 DC	1	piece
2CSS200911R0003	S2C-UA 48 AC Undervoltage release S	S2C-UA 48 AC Undervoltage release S2C-UA 48 AC		
2CSS200910R0005	S2C-OVP1 Overvoltage release	S2C-OVP1	1	piece
2CSS200993R0005	S2C-OVP2 Overvoltage release	S2C-OVP2	1	piece
2CSF200997R0013	F2C-CM Motor operating device	F2C-CM	1	piece
2CSF200996R0013	F2C-ARI Auto-reclosing unit	F2C-ARI	1	piece
2CSF200995R0013	F2C-ARI30 Auto-reclosing unit	F2C-ARI30	1	piece
2CSF200992R0005	F2C-ARH Auto-reclosing unit	F2C-ARH	1	piece
2CSF200991R0005	F2C-ARH -T Auto-reclosing unit with autotest	F2C-ARH -T	1	piece

Categories

 $Low\ Voltage\ Products\ and\ Systems \rightarrow Modular\ DIN\ Rail\ Products \rightarrow Residual\ Current\ Devices\ RCDs \rightarrow Residual\ Current\ Devices\ RCDs$







4