

PRODUCT-DETAILS

## F202 B-25/0.3 F202 B-25/0.3 Residual Current Circuit Breaker 2P B type 300 mA



General Information	
Extended Product Type	F202 B-25/0.3
Product ID	2CSF202568R3250
EAN	8012542341659
Catalog Description	F202 B-25/0.3 Residual Current Circuit Breaker 2P B type 300 mA
Long Description	The RCCBs F200 series assures protection to people and installations against fault current to earth. This product is manufactured according to international IEC standards, for the markets where it is required.
Circular Value Circular Design Principles	Design for Closing Resource Loops - Standard EN45555 - 51,4 %
Recyclability Rate	Design for Closing Resource Loops - Standard En40000 - 31,4 //
Sustainable Material Content	0 %
End of Life Instructions	9AKK108468A4363
Eco Transparency	
Environmental Product Declaration - EPD	9AKK108467A3700

Technical	
Standards	IEC/EN 61008
Type of Residual Current	B type
Rated Voltage (U <sub>r</sub> )	230 V
Rated Operational Voltage	230 V
Rated Insulation Voltage (U <sub>i</sub> )	440 V
Test Voltage (Ut)	170-253 V AC
Rated Impulse Withstand Voltage (U <sub>imp</sub> )	4 kV
Dielectric Test Voltage	2500 V
Input Voltage Type	AC
Rated Current (I <sub>n</sub> )	25 A
Rated Residual Current	300 mA
Rated Residual Breaking Capacity (IΔm)	1 kA
Rated Conditional Short- Circuit Current (I <sub>nc</sub> )	10 kA
Impulse Current	I (max, 8 / 20 μs) 3000 A
Maximum Surge Current	3 kA
Rated Frequency (f)	50 60 Hz
Power Loss	1.58 W
Electrical Endurance	10000 cycle
Mechanical Endurance	20000 cycle
Number of Poles	2
Number of Modular Spacings per DIN Rail	2
Operating Characteristic	Instantaneous (APR High Immunity)
Overvoltage Category	III
Tightening Torque	2.8 N·m
Delay Time (T)	10 ms
Accessory Type	Auxiliary contact, Signal contact/auxiliary contact, Shunt trip, Undervoltage release, Overvoltage release, Motor operating device, Auto reclosing unit
Mounting Type	DIN-Rail
Screw Terminal Type	Failsafe Bi-directional Cylinder-lift Terminal
Options Provided	None
Mounting Position	Any
Accessories Available	Yes
Number of Batteries	0
Cable Size	25 mm²
Connecting Capacity	Busbar 10 mm² Flexible 1 25 mm² Stranded 1 25 mm²
Rated Cross-Section	1 - Solid-Core 1 25 mm²
Wire Stripping Length	12 mm
Terminal Type	Screw Terminals

F202 B-25/0.3 3

Environmental	
Ambient Air Temperature	Operation -25 +70 °
Degree of Protection	Housing IPX Terminals IP2
Pollution Degree	
Environmental Conditions	28 cycle with 55 °C / 90-96 ° and 25 °C / 95-100 °
Resistance to Vibrations acc. to IEC 60068-2-6	0.1 mm or 1 g - 20 cycles at 51505 H
Resistance to Shock acc. to IEC 60068-2-27	25g 2 shocks 13 m
RoHS Status	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 201
RoHS Information	9AKK106713A561
REACH Declaration	9AKK108467A948
Conflict Minerals Reporting Template (CMRT)	9AKK108468A336
Dimensions	
Width in Number of Modular Spacings	
Product Net Width	35 mi
Product Net Height	85 mr
Product Net Depth / Length	69 mi
Product Net Weight	0.220 k
Built-In Depth (t <sub>2</sub> )	69 mr
Ordering	
Minimum Order Quantity	1 piec
Package Level 1 Units	box 1 piec
Package Level 1 Gross Weight	0.236 k
Customs Tariff Number	8536303
E-Number (Finland)	321406
E-Number (Sweden)	216015
Country of Origin	Italy (IT
Certificates and Declarations	
Declaration of Conformity	9AKK106713A561

Data Sheet, Technical Information	9AKK107991A7569
Instructions and Manuals	9AKK107992A0195

Classifications			
ETIM 8	EC000003 - Residual current circuit breaker (RCCB		
ETIM 9	EC000003 - Residual current circuit breaker (RCCB)		
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)		
WEEE B2C / B2B	Business To Consumer		
CN8	85363030		
eClass	V11.0 : 27142201		
Object Classification Code	F		

Accessories				
Identifier	Description	Туре	Quantity	Unit Of Measure
2CDS200912R0001	S2C-H6R Auxiliary Contact	S2C-H6R	2	piece
2CDS200922R0001	S2C-S/H6R Signal / Auxiliary Contact	S2C-S/H6R	2	piece
2CDS200946R0001	S2C-H6-11R Auxiliary Contact	S2C-H6-11R	1	piece
2CDS200946R0003	S2C-H6-02R Auxiliary Contact	S2C-H6-02R	1	piece
2CDS200946R0002	S2C-H6-20R Auxiliary Contact	S2C-H6-20R	1	piece
2CSS200933R0011	F2C-A1 Shunt trip	F2C-A1	1	piece
2CSS200933R0012	F2C-A2 Shunt trip	F2C-A2	1	piece
2CSS200911R0005	S2C-UA 230 AC Undervoltage release	S2C-UA 230 AC	1	piece
2CSS200911R0007	S2C-UA 24 DC Undervoltage release S	S2C-UA 24 DC	1	piece
2CSS200911R0002	S2C-UA 24 AC Undervoltage release S2C-UA 24 AC		1	piece
2CSS200911R0008	S2C-UA 48 DC Undervoltage release \$	S2C-UA 48 DC	1	piece
2CSS200911R0004	S2C-UA 110 AC Undervoltage release	S2C-UA 110 AC	1	piece
2CSS200911R0006	S2C-UA 400 AC Undervoltage release	S2C-UA 400 AC	1	piece
2CSS200911R0001	S2C-UA 12 DC Undervoltage release S2C-UA 12 DC			piece
2CSS200911R0010	S2C-UA 230 DC Undervoltage release	S2C-UA 230 DC	1	piece
2CSS200911R0009	S2C-UA 110 DC Undervoltage release	S2C-UA 110 DC	1	piece
2CSS200911R0003	S2C-UA 48 AC Undervoltage release S2C-UA 48 AC		1	piece
2CSS200910R0005	S2C-OVP1 Overvoltage release	S2C-OVP1	1	piece
2CSS200993R0005	S2C-OVP2 Overvoltage release	S2C-OVP2	1	piece
2CSF200997R0013	F2C-CM Motor operating device	F2C-CM	1	piece
2CSF200996R0013	F2C-ARI Auto-reclosing unit	F2C-ARI	1	piece

## Categories

 $Low\ Voltage\ Products\ and\ Systems\ \to\ Modular\ DIN\ Rail\ Products\ \to\ Residual\ Current\ Devices\ RCDs\ \to\ Residual\ Resi$ 





