High Current Multilayer Chip Power Inductor L-DMI



Overview


KEMET L-DMI ferrite-based Multilayer Chip Power Inductors are ideal for use in DC to DC switching power supplies. The small size of this chip inductor makes it suitable for mobile equipement that requires tight space both in dimension and in height. The internal printed coil structure creates a closed magnetic circuit, which acts as a magnetic shield eliminating crosstalk, thus permitting higher mounting densities. The multilayer block structure yields higher reliability. In addition, the inductor shows excellent low DC power dissipation, due to low Rdc with a high aspect ratio internal conductor that stands on unique green sheet and printing technologies.

Applications

- · Switching DC-DC power supplies
- Wearables
- Smartphone
- · Tablet device
- · Digital still camera
- HDD

Benefits

- · Unique green sheet and printing technologies
- · High reliability
- · High current
- · Low DCR
- Inductance value from 0.47 4.7 μH
- Rated current range from 0.65 1.8 A
- Operating temperature range from -40°C to +85°C
- · Low profile 1.2 mm maximum




Part Number System

| L | 0603 | С | 1R0 | M | DMI | T |
|----------|--|--|---|-------------------------|--|-----------------|
| Inductor | EIA Case Size (L" x W") | Specification | Inductance Value (µH) | Inductance Tolerance | Series | Packaging |
| | 0603 (1608 in mm) 0805 (2012 in mm) 0806 (2016 in mm) 1008 (2520 in mm) | C = Commercial L = 0.8 mm maximum height S = High saturation type Q = 1.2 mm maximum height | R = decimal point Examples: R47 = 0.47 µH 1R0 = 1.0 µH | M = ±20% | DMI = High current multilayer chip type | T = Tape & Reel |



Dimensions - Millimeters (Inches)



Performance Characteristics

| ltem | Performance Characteristics |
|-----------------------------------|-----------------------------|
| Operating Temperature Range | -40°C to +85°C |
| Rated Inductance Range | 0.47 - 4.7 μH |
| Inductance Tolerance | ±20% |
| Inductance Measurement Condition | 1 MHz |
| Rated Current Range | 0.65 - 1.8 A |
| Rated DC Resistance Range Typical | 0.04 - 0.27 Ω |
| Rated DC Resistance Range Maximum | 0.05 – 0.3 Ω |



Environmental Compliance

All KEMET Chip Inductors are RoHS and REACH Compliant.







Table 1 – Ratings & Part Number Reference


| Part Number Inductance (µH) at 1 MHz | | Inductance Tolerance | DC Resistance (Ω) Typical | DC Resistance (Ω) Maximum | Rated Current (A) Maximum ¹ | |
|--------------------------------------|-----------------------------|-------------------------|------------------------------|------------------------------|---|--|
| L0603CR50MDMIT | 0.5 | ±20% | 0.12 | 0.15 | 0.9 | |
| L0603C1R0MDMIT | 1.0 | ±20% | 0.17 | 0.2 | 0.75 | |
| L0603C2R2MDMIT | 2.2 | ±20% | 0.27 | 0.3 | 0.65 | |
| L0805CR47MDMIT | 0.47 | ±20% | 0.06 | 0.08 | 1.2 | |
| L0805C1R0MDMIT | 1.0 | ±20% | 0.11 | 0.14 | 1 | |
| L0805C1R5MDMIT | 1.5 | ±20% | 0.15 | 0.2 | 0.8 | |
| L0805C2R2MDMIT | 2.2 | ±20% | 0.15 | 0.2 | 0.8 | |
| L0805C3R3MDMIT | 3.3 | ±20% | 0.2 | 0.24 | 0.7 | |
| L0805C4R7MDMIT | 4.7 | ±20% | 0.23 | 0.28 | 0.7 | |
| L0806CR47MDMIT | 0.47 | ±20% | 0.06 | 0.075 | 1.6 | |
| L0806C1R0MDMIT | 1.0 | ±20% | 0.09 | 0.12 | 1.3 | |
| L0806C1R5MDMIT | 1.5 | ±20% | 0.1 | 0.13 | 1.2 | |
| L0806C2R2MDMIT | 2.2 | ±20% | 0.11 | 0.14 | 1.2 | |
| L0806C3R3MDMIT | 3.3 | ±20% | 0.13 | 0.16 | 1.1 | |
| L0806C4R7MDMIT | 4.7 | ±20% | 0.16 | 0.2 | 0.9 | |
| L1008CR47MDMIT | 0.47 | ±20% | 0.04 | 0.05 | 1.8 | |
| L1008C1R0MDMIT | 1.0 | ±20% | 0.07 | 0.08 | 1.4 | |
| L1008C1R5MDMIT | 1.5 | ±20% | 0.08 | 0.09 | 1.3 | |
| L1008C2R2MDMIT | 2.2 | ±20% | 0.08 | 0.09 | 1.3 | |
| L1008C3R3MDMIT | 3.3 | ±20% | 0.09 | 0.12 | 1.2 | |
| L1008C4R7MDMIT | 4.7 | ±20% | 0.12 | 0.15 | 1.1 | |
| L1008L1R5MDMIT | 1.5 | ±20% | 0.08 | 0.09 | 1.3 | |
| L1008L2R2MDMIT | 2.2 | ±20% | 0.08 | 0.1 | 1.2 | |
| L1008S1R0MDMIT | 1.0 | ±20% | 0.09 | 0.115 | 1.2 | |
| L1008S2R2MDMIT | 2.2 | ±20% | 0.09 | 0.115 | 1.2 | |
| L1008S4R7MDMIT | 4.7 | ±20% | 0.14 | 0.16 | 1.1 | |
| L1008Q1R0MDMIT | 1.0 | ±20% | 0.09 | 0.12 | 1.2 | |
| L1008Q2R2MDMIT | 2.2 | ±20% | 0.12 | 0.15 | 1.1 | |
| L1008Q3R3MDMIT | 3.3 | ±20% | 0.11 | 0.15 | 1.1 | |
| L1008Q4R7MDMIT | 4.7 | ±20% | 0.14 | 0.16 | 1.1 | |
| Part Number | Inductance (µH) at 1 MHz | Inductance Tolerance | DC Resistance (Ω) Typical | DC Resistance (Ω) Maximum | Rated Current (A) Maximum ¹ | |


¹ T = 40 K rise at rated current at 20°C




































































































Taping Specifications - Millimeters (Inches)

0603 Paper Tape 8mm Width




| EIA | Metric Case Size | Height | Reel | | Car | vity . | Pitch | Thickness |
|-----------|---------------------|--------|----------|-----------|------|--------|-------|-----------|
| Case Size | | | Quantity | | A | В | Р | T |
| | | | | Nominal | 1.0 | 1.8 | 4.0 | 1.1 |
| 0603 | 1608 | 0.8 | 4,000 | Tolerance | ±0.2 | ±0.2 | ±0.1 | Maximum |



Taping Specifications - Millimeters (Inches) cont.


0805, 0806, 1008 Embossed (Plastic) Tape 8mm Width



| EIA | Metric | Hainht | Reel | | Cavity | | Pitch | Thickness | | |
|-----------|-----------|--------|-----------|-----------|-----------|------|-------|-----------|------|-----|
| Case Size | Case Size | Height | Quantity | | Α | В | Р | T | K | |
| 2225 | | 3,000 | Nominal | 1.55 | 2.30 | 4.00 | 0.30 | 1.3 | | |
| 0805 2012 | 0.9 | | Tolerance | ±0.2 | ±0.2 | ±0.1 | | | | |
| | 2016 | 0.9 | 3,000 | Nominal | 1.80 | 2.20 | 4.00 | 0.25 | 1.3 | |
| 0806 | | | | Tolerance | ±0.1 | ±0.1 | ±0.1 | | | |
| 1008 | 2520 | 0.7 | 3,000 | Nominal | 2.3 | 2.8 | 4 | 0.00 | 1.4 | |
| | | | 0.9 | 3,000 | Tolerance | ±0.1 | ±0.1 | ±0.1 | 0.30 | 1.4 |
| | | | | Nominal | 2.30 | 2.80 | 4.00 | | | |
| | | | 1.1 | 2,000 | Tolerance | ±0.1 | ±0.1 | ±0.1 | 0.30 | 1.7 |




Reel Specifications - Millimeters



| Series | | | | Millimeters | | | | | |
|--------|-----------|--------|---------|-------------|-------|------|-----|---------|------|
| | | Α | В | С | D | E | R | t | W |
| L-DMI | Nominal | ø178.0 | ø60.0 | ø13.0 | ø21.0 | 2.0 | 1.0 | 2.5 | 10.0 |
| | Tolerance | ±2.0 | Minimum | ±0.2 | ±0.8 | ±0.5 | | Maximum | ±1.5 |



Recommended Reflow Soldering Profile



Handling Precautions

Inductors should be stored in normal working environments. While the inductors themselves are quite robust in other environments, exposure to high temperatures, high humidity, corrosive atmospheres, and long-term storage degrades solderability.

KEMET recommends that maximum storage temperature not exceed 40°C and maximum storage humidity not exceed 70% relative humidity. Atmospheres should be free of chlorine-bearing and sulfur-bearing compounds. Temperature fluctuations should be minimized to avoid condensation on the parts.

For optimized solderability, inductor stock should be used promptly, preferably within six months of receipt.

High Current Multilayer Chip Power Inductor L-DMI

OBSOLETE



KEMET Electronics Corporation Sales Offices

For a complete list of our global sales offices, please visit www.kemet.com/sales.

Disclaimer

YAGEO Corporation and its affiliates do not recommend the use of commercial or automotive grade products for high reliability applications or manned space flight.

All product specifications, statements, information and data (collectively, the "Information") in this datasheet are subject to change. The customer is responsible for checking and verifying the extent to which the Information contained in this publication is applicable to an order at the time the order is placed. All Information given herein is believed to be accurate and reliable, but it is presented without guarantee, warranty, or responsibility of any kind, expressed or implied.

Statements of suitability for certain applications are based on KEMET Electronics Corporation's ("KEMET") knowledge of typical operating conditions for such applications, but are not intended to constitute – and KEMET specifically disclaims – any warranty concerning suitability for a specific customer application or use. The Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by KEMET with reference to the use of KEMET's products is given gratis, and KEMET assumes no obligation or liability for the advice given or results obtained.

Although KEMET designs and manufactures its products to the most stringent quality and safety standards, given the current state of the art, isolated component failures may still occur. Accordingly, customer applications which require a high degree of reliability or safety should employ suitable designs or other safeguards (such as installation of protective circuitry or redundancies) in order to ensure that the failure of an electrical component does not result in a risk of personal injury or property damage.

Although all product-related warnings, cautions and notes must be observed, the customer should not assume that all safety measures are indicated or that other measures may not be required.

When providing KEMET products and technologies contained herein to other countries, the customer must abide by the procedures and provisions stipulated in all applicable export laws and regulations, including without limitation the International Traffic in Arms Regulations (ITAR), the US Export Administration Regulations (EAR) and the Japan Foreign Exchange and Foreign Trade Act.