

# WL12C-3P2432A00

W12-3

**SMALL PHOTOELECTRIC SENSORS** 





### Ordering information

Туре	Part no.
WL12C-3P2432A00	1067774

Other models and accessories → www.sick.com/W12-3

Illustration may differ



### Detailed technical data

### **Features**

Functional principle	Photoelectric retro-reflective sensor
Functional principle detail	Autocollimation
Sensing range max.	0 m 5 m <sup>1)</sup>
Sensing range	0 m 4 m <sup>1)</sup>
Polarisation filters	Yes
Emitted beam	
Light source	PinPoint LED <sup>2)</sup>
Type of light	Visible red light
Light spot size (distance)	Ø 100 mm (3 m)
Key LED figures	
Wave length	640 nm
Adjustment	IO-Link, Single teach-in button
Angle of dispersion	Approx. 1.5°
Pin 2 configuration	External input, Teach-in input, Sender off input, Detection output, logic output, Device contamination alarm output

<sup>1)</sup> Reflector PL80A.

### Safety-related parameters

MTTF <sub>D</sub>	891 years
DC <sub>avg</sub>	0 %
T <sub>M</sub> (mission time)	20 years

 $<sup>^{2)}</sup>$  Average service life: 100,000 h at TU = +25 °C.

### Communication interface

IO-Link	<b>√</b> , COM2 (38,4 kBaud)
Data transmission rate	COM2 (38,4 kBaud)
Cycle time	2.3 ms
Process data length	16 Bit
Process data structure	Bit 0 = switching signal $Q_{L1}$ Bit 1 = switching signal $Q_{L2}$ Bit 2 15 = empty
VendorID	26
DeviceID HEX	0x8000EE
DeviceID DEC	8388846

### Electrical data

Liooti iodi data	
Supply voltage U <sub>B</sub>	10 V DC 30 V DC <sup>1)</sup>
Ripple	< 5 V <sub>pp</sub> <sup>2)</sup>
Current consumption	30 mA <sup>3)</sup>
Protection class	III
Digital output	
Туре	PNP <sup>4)</sup>
Switching mode	Light/dark switching
Signal voltage PNP HIGH/LOW	> Uv - 2,5 V / ca. 0 V
Output current I <sub>max.</sub>	≤ 100 mA
Response time	5)
Repeatability (response time)	100 μs <sup>6)</sup>
Switching frequency	1,500 Hz <sup>7)</sup>
Circuit protection	A <sup>8)</sup> B <sup>9)</sup> C <sup>10)</sup> D <sup>11)</sup>
Response time Q/ on Pin 2	200 μs 300 μs <sup>5) 6)</sup>
Switching frequency Q / to pin 2	≤ 1,500 Hz <sup>12)</sup>

 $<sup>^{1)}</sup>$  Limit values when operated in short-circuit protected network: max. 8 A.

### Mechanical data

Housing	Rectangular
Dimensions (W x H x D)	15.6 mm x 48.5 mm x 42 mm

 $<sup>^{2)}\,\</sup>text{May}$  not exceed or fall below  $\text{U}_{\text{V}}$  tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Pin 4: This switching output must not be connected to another output.

 $<sup>^{5)}</sup>$  Signal transit time with resistive load.

 $<sup>^{6)}</sup>$  Valid for Q \ on Pin2, if configured with software.

 $<sup>^{7)}</sup>$  With light/dark ratio 1:1.

 $<sup>^{8)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

 $<sup>^{9)}</sup>$  B = inputs and output reverse-polarity protected.

<sup>10)</sup> C = interference suppression.

 $<sup>^{11)}</sup>$  D = outputs overcurrent and short-circuit protected.

 $<sup>^{12)}</sup>$  With light / dark ratio 1:1, valid for Q  $\backslash$  on Pin2, if configured with software.

### SMALL PHOTOELECTRIC SENSORS

Connection	Male connector M12, 4-pin
Material	
Housing	Metal, zinc diecast
Front screen	Plastic, PMMA
Weight	120 g

### Ambient data

Enclosure rating	IP66 IP67
Ambient operating temperature	-40 °C +60 °C
Ambient temperature, storage	-40 °C +75 °C
UL File No.	NRKH.E181493 & NRKH7.E181493

### **Smart Task**

omare room		
Smart Task name	Base logics	
Logic function	Direct AND OR WINDOW Hysteresis	
Timer function	Deactivated On delay Off delay ON and OFF delay Impulse (one shot)	
Inverter	Yes	
Switching frequency	SIO Direct: 1500 Hz <sup>1)</sup> SIO Logic: 1500 Hz <sup>2)</sup> IOL: 1100 Hz <sup>3)</sup>	
Response time	SIO Direct: 200 $\mu$ s 300 $\mu$ s $^{1)}$ SIO Logic: 400 $\mu$ s 500 $\mu$ s $^{2)}$ IOL: 400 $\mu$ s 750 $\mu$ s $^{3)}$	
Repeatability	SIO Direct: $100 \ \mu s^{\ 1)}$ SIO Logic: $100 \ \mu s^{\ 2)}$ IOL: $350 \ \mu s^{\ 3)}$	
Switching signal		
Switching signal $Q_{L1}$	Switching output	
Switching signal Q <sub>L2</sub>	Switching output	

<sup>1)</sup> SIO Direct: sensor operation in standard I/O mode without IO-Link communication and without using internal sensor logic or time parameters (set to "direct"/"deactivated").

### Diagnosis

Device status	Yes
Quality of teach	Yes
Quality of run	Yes, Contamination display

### Classifications

ECLASS 5.0	27270902
------------	----------


<sup>2)</sup> SIO Logic: Sensor operation in standard I/O mode without IO-Link communication. Sensor-internal logic or timing parameters plus Automation Functions used.

 $<sup>^{3)}</sup>$  IOL: Sensor operation with full IO-Link communication and usage of logic, timing and Automation Function parameters.


ECLASS 5.1.4	27270902
ECLASS 6.0	27270902
ECLASS 6.2	27270902
ECLASS 7.0	27270902
ECLASS 8.0	27270902
ECLASS 8.1	27270902
ECLASS 9.0	27270902
ECLASS 10.0	27270902
ECLASS 11.0	27270902
ECLASS 12.0	27270902
ETIM 5.0	EC002717
ETIM 6.0	EC002717
ETIM 7.0	EC002717
ETIM 8.0	EC002717
UNSPSC 16.0901	39121528

### Connection diagram

### Cd-367




### Characteristic curve




- ① Reflector PL80A
- ② Reflector C110A
- ③ Reflector PL20A
- ④ Reflective tape

### Sensing range diagram



- ① Reflective tape
- ② Reflector PL20A
- 3 Reflector PL30A
- Reflector PL40A
- ⑤ Reflector PL50A
- ® Reflector C110A
- ⑦ Reflector PL80A

### Dimensional drawing (Dimensions in mm (inch))



- ① Optical axis
- ② LED indicator yellow: Status of received light beam
- 3 LED indicator green: Supply voltage active
- ④ M4 threaded mounting hole, 4 mm deep
- ⑤ Mounting hole, Ø 4.2 mm
- ⑤ Sensitivity setting: single teach-in button
- $\ensuremath{\ensuremath{\,\bigcirc}}$  Connection

### Recommended accessories

Other models and accessories → www.sick.com/W12-3

	Brief description	Туре	Part no.		
Mounting brackets and plates					
	Universal mounting bracket for reflectors, steel, zinc coated	BEF-WN-REFX	2064574		
Plug connectors and cables					
	<ul> <li>Connection type head A: Female connector, M12, 4-pin, straight, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 5 m, 4-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals</li> </ul>	YF2A14- 050VB3XLEAX	2096235		
	<ul> <li>Connection type head A: Male connector, M12, 4-pin, straight</li> <li>Description: Unshielded</li> <li>Connection systems: Screw-type terminals</li> <li>Permitted cross-section: ≤ 0.75 mm²</li> </ul>	STE-1204-G	6009932		

## WL12C-3P2432A00 | W12-3

### SMALL PHOTOELECTRIC SENSORS

	Brief description	Туре	Part no.
Reflectors			
	Rectangular, screw connection, 18 mm x 60 mm, PMMA/ABS, Screw-on, 2 hole mounting	PL20A	1012719

### Recommended services

Additional services → www.sick.com/W12-3

	Туре	Part no.
Function Block Factory		
<ul> <li>Description: The Function Block Factory supports common programmable logic controllers (PLCs) from various manufacturers, such as Siemens, Beckhoff, Rockwell Automation and B&amp;R. More information on the FBF can be found <a href="https://fbf.cloud.sick.com" target="_blank">here</a>.</li> <li>Note: You can configure your function block at <a href="https://fbf.cloud.sick.com" target="_blank">Function Block Factory.</a> As a login please use your SICK ID.</li> </ul>	Function Block Factory	On request

### SICK AT A GLANCE

SICK is one of the leading manufacturers of intelligent sensors and sensor solutions for industrial applications. A unique range of products and services creates the perfect basis for controlling processes securely and efficiently, protecting individuals from accidents and preventing damage to the environment.

We have extensive experience in a wide range of industries and understand their processes and requirements. With intelligent sensors, we can deliver exactly what our customers need. In application centers in Europe, Asia and North America, system solutions are tested and optimized in accordance with customer specifications. All this makes us a reliable supplier and development partner.

Comprehensive services complete our offering: SICK LifeTime Services provide support throughout the machine life cycle and ensure safety and productivity.

For us, that is "Sensor Intelligence."

### **WORLDWIDE PRESENCE:**

Contacts and other locations -www.sick.com

