

RoHS
Compliant



Description

This solder thermometer is capable of measuring the temperature of a soldering tip up to $\pm 5^{\circ}\text{C}$. The ST-1090 features a 3-point thermocouple sensor which is able to measure regardless of the angle of the soldering iron.

This thermometer also features a MAX HOLD function to display the highest recorded temperature and is able to send measurements to a PC via a USB connection. Further more, the MPro MP741058 will give automatic warnings when the sensor needs to be replaced (after about 50 times) and when the battery is running low. At last, a K-type thermocouple is supplied with the thermometer to do some external measurements.

Features

- Large LCD screen.
- Accurate temperature measurement 0°C to 800°C .
- Performance stable and easy to operate.
- IR temperature calibration.
- USB communication function.
- Automatic shut down function.

Specifications

Resolution	: $1^{\circ}\text{C}/1^{\circ}\text{F}$
Temperature range	: 0°C to $800^{\circ}\text{C}/32^{\circ}\text{F}$ to 1472°F
Operating environment	: 0°C to $40^{\circ}\text{C}/32^{\circ}\text{F}$ to 104°F
Temperature resolution	: 1°C
Temperature accuracy	: $\pm 5^{\circ}\text{C}$
Temperature sensor type	: K-type thermocouple
Power supply	: 9V battery (not included)
Dimensions	: $75\text{mm} \times 143.5\text{mm} \times 41.5\text{mm}$
Weight	: 185g
Warranty	: 03 years

Part Number Table

Description	Part Number
Soldering Tip Thermometer, $75\text{mm} \times 143.5\text{mm} \times 41.5\text{mm}$	MP741058

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.