

### DLW21SH670HQ2#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of DLW21SH670HQ2# from the official website of Murata

http://www.murata.com/en-gb/products/productdetail?partno=DLW21SH670HQ2%23

"#"at the end indicates the package specification code.









< List of part numbers with package codes > DLW21SH670HQ2B DLW21SH670HQ2L



### **Applications**

Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
Specific Applications	Automotive powertrain/safety equipment, Automotive infotainment/comfort equipment,Medical equipment [GHTF A/B/C] except for implant & surgery & auto injector Please refer to Our Website and specifications, etc. for information about the performance, functions, quality, management, and safety required for the above applications, and use Products after confirming the	
	performance and reliability of the actual	
	Product.	
Recommended	Automotive powertrain/safety equipment,	
Applications	LVDS	



### **Packaging Information**

		Standard
Packaging	Specifications	Packing
		Quantity
В	Bulk(Bag)	500
L	180mm Embossed Tape	2000



### **Features**


- 1. Small size: 2.0x1.2x1.2mm
- 2. Available for high density mounting (Narrow pitch)
- ■Application

Common mode noise suppression for automotive interfaces such as USB,LVDS,PCIe



# Appearance & Shape





1 of 3

#### Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





# DLW21SH670HQ2#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of DLW21SH670HQ2# from the official website of Murata

http://www.murata.com/en-gb/products/productdetail?partno=DLW21SH670HQ2%2

"#"at the end indicates the package specification code.



# **Specifications**

Shape	SMD
Size Code (in mm)	2012
Size Code (in inch)	0805
Length	2.0mm
Length Tolerance	±0.2mm
Width	1.2mm
Width Tolerance	±0.2mm
Thickness	1.2mm
Thickness Tolerance	±0.2mm
Common Mode Impedance (at 100MHz)	67Ω
Common Mode Impedance (at 100MHz) Tolerance	±25%
Rated Current	320mA
Derating of Rated Current	Yes (Over 105°C) *For details, please check the derating diagram.
Rated Voltage	20Vdc
Withstanding Voltage	50Vdc
DC Resistance(max.)	0.312Ω
DC Resistance	0.24Ω±30%
Insulation Resistance(min.)	10ΜΩ
Operating Temperature Range	-40°C to 125°C
Mass(typ.)	0.011g
Number of Circuit	1
Operating Temperature Range(Self-temperature rise is included)	No

Brand	Murata

2 of 3

#### Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- $2. This \ data{sheet has only typical specifications because there is no \ space for \ detailed \ specifications.}$
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.




### DLW21SH670HQ2#


Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of DLW21SH670HQ2# from the official website of Murata

"#"at the end indicates the package specification code.

# **Product Data**






### Impedance-Frequency Characteristics

In operating temperature exceeding +105°C, derating of current is necessary for this series.


Please apply the derating curve shown in chart according to the operating temperature.

#### Derating of Rated Current




Impedance-Frequency Characteristics (Main Items)

#### ■ Equivalent Circuit (Note 1)



Note1: The Port/Pin No. of the Simulation Model provided by our company is



**Equivalent Circuit** 

**Derating of Rated Current** 

3 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

