



^{EST} 1984










RoHS Compliant



PX-101

LP PCle 1+1xRS232 1MBaud

"SERIAL CARDS ENGINEERED TO EXCEED EXPECTATIONS"



Features

- 1+1 port RS232
- PCI Express x1, x4, x8 & x16 lane slots socket size
- 256 Byte Tx and 256 Byte Rx FIFOs
- Up to 921,600 Baud
- DB9 connector (9 Pin Male)
- Drivers for all popular operating systems
- Sample Programs, Test & Terminal software
- Lifetime Support
- Lifetime Warranty (registration required)

Options



PX-101: LP PCle 1+1xRS232 1MBaud

Description

PCI Express Card providing two RS232 serial ports. Low profile board gives first serial port on the bracket, with a second serial port on a fly lead. Up to 921,600 data transfer rates and the 256 byte deep transmit and 256 byte receive FIFOS, coupled with 1Mbit/s line drivers deliver uncompromising performance on your PC.

PCI Express is the latest standard in PC connectivity.

With Brainboxes' industry renowned Lifetime Warranty and Lifetime Support! Low profile board gives first serial port on the bracket, with a second port on a fly lead.

Software

Microsoft signed drivers (easy installation & robust operation) for:

- Windows Server 2008 32 bit & 64 bit Editions
- Windows Vista 32 bit and 64 bit editions
- Windows Server 2003 32 bit & 64 bit Editions
- Windows XP 32 bit & 64 bit editions

As well as: full product documentation, a thorough troubleshooting guide and terminal software. Detailed sample source code for many popular programming languages. Further OS support on next page.

























ORDER Description

LP PCIe 1+1xRS232 1MBaud

Code PX-101

*For standard profile see PX-257 - max baud rate is driver dependant



LP PCle 1+1xRS232 1MBaud

PX-101: Full Specification

PX-101: Full Specification		
Port	Ports	1+1 x RS232
Pin 1 DCD RS232 Pinout (9 pin Male)	Connector	DB9 connector (9 Pin Male)
Pin 2 RXD 1 5 Pin 3 TXD 1 5	FIFO size	256 RX FIFO + 256 TX FIFO
Pin 4 DTR Pin 5 GND	Operating Distance	EIA - RS232 Standard
Pin 6 DSR Pin 7 RTS Pin 8 CTS Pin 9 RI 6 9	Cable	1 PORT RS232 on fly lead
Port Settings	Baud Rate	921,600
921,600	Data Bits	5,6,7 or 8
>>> >	Parity	Odd, Even, None, Mark or Space
baud	Stop Bits	1, 1.5 or 2
	Flow Control	RTS/CTS DSR/DTR XON/XOFF
	Tx/Rx Modes	Point to Point
	OS Compatibility	Windows Server 2008 32 bit & 64 bit Editions
Interface	O3 Compatibility	Windows Vista 32 bit & 64 bit Editions
PCI>>> EXPRESS*		Windows Server 2003 32 bit & 64 bit Editions
EXPRESS		Windows XP 32 bit & 64 bit Editions Microsoft Windows 2000
	BUS	
A I .	Other Approvals	PCI Express x1, x4, x8 & x16 lane slots : WEEE ROHS METL EMC: CE
Approvals		
ROHS	Microsoft Approvals	Microsoft Certified Gold Partner Windows Server 2008 32 bit & 64 bit editions Windows Vista 32 bit & 64 bit editions
		Windows Server 2003 32 bit & 64 bit editions Windows XP 32 bit & 64 bit editions
General	PCB Layers	4
	Power Consumption	380mA @ 3.3V
	Weight	0.046 Kg
	Size	130x20x80 mm
Box Content	Packaging	Installation CD including manual, Microsoft signed drivers & utilities
	Card	LP PCIe 1+1xRS232 1MBaud /
		1 PORT RS232 on fly lead
Product Support	Warranty	Lifetime (online registration required)
	Support	Lifetime Web, Email and Phone Support from fully qualified, friendly staff who work in and alongside the Product Development Team
Additional	OEM option	Available for bulk buy OEM
Elektra O5 European Electronics Industry wards	Made In	Manufactured in the UK by Brainboxes Winner 2005 European Electronics Industry Awards "Manufacturer of the Year"
WINNER Manufacturer of the Year Made in the UK	Customisable	Brainboxes operate a "Perfect Fit Custom Design" policy for volume users. More Info: sales@brainboxes.com

Datasheet Version: 3.79 Published on: 2009/8/25