# Surface Mount Zener Diode





### Features:

- Planar Die Construction
- 350mW Power Dissipation
- · General Purpose, Medium Current
- Ideally Suited For Automated Assembly Processes

# SOT-23 CONNECTION DIAGRAM 3 1 2 NC

### Application:

350mW Surface mount zener diode

### Maximum Rating @ TA = 25°C unless otherwise specified

Characteristic	Symbol	Value	Unit
Forward voltage @ I <sub>F</sub> = 10mA	V <sub>F</sub>	0.9	V
Power dissipation	P <sub>D</sub>	350	mW
Thermal resistance, junction to ambient air	$R_{\theta j A}$	357	°C/W
Operating and storage temperature range	T <sub>j</sub> , T <sub>stg</sub>	-65 to +150	°C

**Note :** Valid provided that device terminals are kept at ambient temperature. Tested with pulses,  $T_p \le 1 ms$ .

### Electrical Characteristics @ TA = 25°C unless otherwise specified

		Zener Voltage Range			Maximum Zener Impedance		Maximum Reverse Leakage Current		
Type Number	Marking Code		V <sub>z</sub> @I <sub>ZT</sub>		I <sub>ZT</sub>	Z <sub>ZT</sub> @I <sub>ZT</sub>	Z <sub>ZK</sub> @I <sub>ZK</sub> = 0.25mA	I <sub>R</sub>	@V <sub>R</sub>
		Nom(V)	Min(V)	Max(V)	(mA)		(Ω)	(μΑ)	(V)
MMBZ5236B	KF1	7.5	7.13	7.88	20	6	500	3	6


www.element14.com www.farnell.com www.newark.com



## **Surface Mount** Zener Diode




### Typical Characteristics @ TA = 25°C unless otherwise specified



### **Package Outline**

Plastic surface mounted package



SOT-23				
Dim	Min	Max		
Α	2.85	2.95		
В	1.25	1.35		
С	1 Typical			
D	0.37	0.43		
E	0.35	0.48		
G	1.85	1.95		
Н	0.02	0.1		
J	0.1 Typical			
K	2.35	2.45		
All Dimensions in mm				


www.element14.com www.farnell.com www.newark.com



# Surface Mount Zener Diode



### **Soldering Footprint**



**Dimensions: Millimetres** 

### **Package Information**

Device	Package	Shipping
MMBZ5236B-7-F	SOT-23	3,000/Tape & Reel

### **Part Number Table**

Description	Part Number	
350mW Surface Mount Zener Diode	MMBZ5236B-7-F	

Important Notice: This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2012.

www.element14.com www.farnell.com www.newark.com

