

AT980D Data Sheet



Model No. AT-980D UK & AT-980D EU

Applicable

- Laboratories
- Production Line
- Communication device maintenance
- Institutes
- Teaching and practice

Features

- High definition LCD display looks splendid.
- Quick temperature storing and retrieving to switch between frequently-used temperatures immediately.
- Designed with excellent and high performance heater to obtain fast thermal recovery.
- Temperatures read in Celsius or Fahrenheit.
- Digital temperature calibration enables easy operation.
- Compatible with international brand tips, convenient to choose tips.

Specifications

Power Consumption	: 80W
Power Source	: 220V AC \pm 10% 50Hz(110V AC 60Hz optional)
Temperature Range	: 150°C to 450°C (302°F to 842°F)
Temperature Stability	: \pm 2°C (still air, no load)
Temperature Accuracy	: \pm 10°C
Tip-to-ground Impedance	: $<$ 2 Ω
Tip-to-ground Potential	: $<$ 2mV
Setting Manner	: Buttons
Temperature Calibration	: Digital Calibration
Heater	: 80W quad-wire ceramic heater
Dimensions	: 146mm(L) \times 120mm(W) \times 91(H)mm
Net weight	: 1.8kg
Operative tips	: 900M series tips(Appendix)

Package List

Main unit	1 Unit
Handle set	1 Pcs
Iron Stand	1 Pcs
Power cord	1 Pcs
Manual	1 Pcs
Cleaning sponge	1 Pcs

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

