LOUDSPEAKER ASSEMBLIES

GENERAL DESCRIPTION

The MA/E5/S7/T1 is a 275 CID, sound masking loudspeaker assembly consisting of an 8C5PAX - 8" O.D. dual cone loudspeaker with a 5 oz. magnet and a TBL70 - 4W-70V transformer. Suspension chain is supplied.

INTENDED USE - Indoor Environment

Program Material Installation

Equalized Random Noise

Suspended by supplied chain mounting hardware between the structural deck and suspended ceiling deck in the following orientations: upwards, downwards or sideways.

AUDIO SPECIFICATIONS

Average Sensitivity **Loudspeaker Power Rating Maximum Power Rating** Calculated Output Magnet Type, Weight | BeFe Ceramic, 4.8 oz Frequency Response Nominal Coverage Angle **Audio Connection**

92 dB-SPL 1W/1M 12W RMS, EIA 426A Standard

15W @ 8 Ohms 98 dB SPL, 4W/ 1M

65 Hz - 17 kHz EIA 426A Standard 90° Included Angle, -6 dB / 2 kHz, Half space

7" Color Coded Leads

Mechanical Connection | Light Steel Chain, 4'-0" Long (supplied)

SYSTEM COMPONENTS

Loudspeaker

Transformer

TBL70 - 4W-70V: 5 Tap, Color Coded Leads

(4W, 2W, 1W, 0.5W, 0.25W)

Baffle

BR8W Enclosure | ERD8U

RECOMMENDED ADDITIONAL QUAM COMPONENTS


Attenuators QC101M, QC101M/RM


MA/E5/S7/T1

SOUND MASKING


275 CID Economy Assembly, 8" O.D. Speaker, **4W-70V Transformer**







Recommended construction sequences, installation instructions, and A&E Specifications are available in various formats in the QUAM Architects' and Engineers' Resources section on the web at: www.QuamSpeakers.com









QUAM-NICHOLS COMPANY, INC. 234 East Marquette Rd. Chicago, IL. 60637 Tel: 1-800-NEED-NOW (800-633-3669) Fax: 1-888-NEED-NOW (888-633-3669) e-mail: NeedNow@QNC.com www.QuamSpeakers.com