

#### **General Information**

MS132-4.0 **Extended Product Type:** 1SAM350000R1008 Product ID: EAN: 4013614400087

**Catalog Description:** MS132-4.0 Manual Motor Starter

The MS132-4.0 manual motor starter is a compact 45 mm width devices with a rated Long Description:

operational current of le = 4.00 A. This device is used to manually switch on and off motors and to protect them reliably and without the need for a fuse from short-circuits, overload and phase failures. The manual motor starter offers a rated service short-circuit breaking capacity Ics = 100 kA at 400 VAC and the trip class 10. Further features are the build-in disconnect function, temperature compensation, trip-free mechanism and a rotary handle with a clear switch position indication. The manual motor starter is suitable for three- and single-phase applications. The handle is lockable to protect against unauthorized changes. Auxiliary contacts, signalling contacts, undervoltage releases, shunt trips, 3-phase bus

bars, power in-feed blocks are available as accessory.

### Categories

Products » Low Voltage Products and Systems » Circuit Breakers » Manual Motor Starters

Products » Low Voltage Products and Systems » Control Products » Manual Motor Starters » Manual Motor Starters

#### Ordering

Minimum Order Quantity: 1 piece **Customs Tariff Number:** 85362010 4013614400087

## **Container Information**

Package Level 1 Width: 92 mm 95 mm Package Level 1 Length: Package Level 1 Height: 50 mm Package Level 1 Gross Weight: 0.28 kg Package Level 2 Units: 40 piece Package Level 2 Width: 280 mm Package Level 2 Length: 395 mm Package Level 2 Height: 210 mm Package Level 2 Gross Weight: 11.586 kg 4013614408984 Package Level 2 EAN: Package Level 1 Units: 1 piece

#### **Dimensions**

**Product Net Height:** 90 mm 86.75 mm **Product Net Depth: Product Net Weight:** 0.265 kg **Product Net Width:** 45 mm

### **Technical**

**Rated Ultimate Short-Circuit** (230 V AC) 100 kA Breaking Capacity (Icu): (400 V AC) 100 kA (440 V AC) 20 kA

(500 V AC) 20 kA (690 V AC) 3 kA

Rated Instantaneous Short-Circuit

Current Setting (Ii):

Rated Operational Voltage:

50 A

Setting Range: 2.5 ... 4 A

Rated Operational Power AC-3 (Pe): (400 V) Three Phase 1.5 kW Main Circuit 690 V AC

Main Circuit 250 V DC

Rated Operational Current (Ie): Rated Operational Current AC-3 (Ie): 4 A Rated Operational Current DC-5 (Ie): 4 A

Main Circuit 50 Hz Rated Frequency (f):

Main Circuit 60 Hz

Rated Impulse Withstand Voltage

(U<sub>imp</sub>):

Rated Insulation Voltage (Ui): 690 V

Main Circuit 6 kV

Power Loss: at Rated Operating Conditions per Pole 0.7 ... 1.8 W

**Number of Poles:** 

Conventional Free-air Thermal

Current (Ith):

Main Circuit 4 A

Degree of Protection: Housing IP20

Main Circuit Terminals IP10

**Pollution Degree:** 

**Electrical Durability:** 50000 cycle **Mechanical Durability:** 100000 cycle

**Connecting Capacity Main Circuit:** Flexible with Ferrule 1/2x 0.75 ... 2.5 mm<sup>2</sup>

Flexible with Insulated Ferrule 1/2x 0.75 ... 2.5 mm<sup>2</sup>

Flexible 1/2x 0.75 ... 2.5 mm<sup>2</sup> Rigid 1/2x 1 ... 4 mm<sup>2</sup>

**Tightening Torque:** Main Circuit 0.8 ... 1.2 N·m

Wire Stripping Length: Main Circuit 9 mm **Recommended Screw Driver:** Pozidriv 2 **Mounting Position:** Position 1 to 6 **Actuator Type:** Rotary Handle ON / OFF / TRIP

**Contact Position Indication:** Mounting on DIN Rail: TH35-15 (35 x 15 mm Mounting Rail) acc. to IEC 60715

TH35-7.5 (35 x 7.5 mm Mounting Rail) acc. to IEC 60715

Standards: IEC/EN 60947-1

> IEC/EN 60947-2 IEC/EN 60947-4-1 UL 60947-1 UL 60947-4-1

**Rated Service Short-Circuit** 

(230 V AC) 100 kA

Breaking Capacity (Ics): (250 V DC) 3 Poles in Series 10 kA

(400 V AC) 100 kA (440 V AC) 20 kA (500 V AC) 20 kA (690 V AC) 3 kA

#### **Environmental**

**Ambient Air Temperature** 

Compensation:

Yes 2000 m

**Maximum Operating Altitude** 

Permissible:

11 ms Pulse 25g

Resistance to Shock acc. to IEC

60068-2-27:

Resistance to Vibrations acc. to IEC 5g / 3 ... 150 Hz

60068-2-6:

**RoHS Status:** 

Following EU Directive 2002/95/EC August 18, 2005 and amendment

**Ambient Air Temperature:** Around the Enclosure 0 ... +40 °C

Operation -25 ... +70 °C

Operation Compensated -25 ... +60 °C

Storage -50 ... +80 °C

## **Technical UL/CSA**

Horsepower Rating UL/CSA: (220 ... 240 V AC) Three Phase 1 Hp

(440 ... 480 V AC) Three Phase 2 Hp (550 ... 600 V AC) Three Phase 3 Hp

Ampere Rating UL/CSA: 4 A

General Use Rating UL/CSA: (600 V AC) 4 A

**Connecting Capacity Main Circuit** 

UL/CSA:

Flexible 1/2x 16-12 AWG Stranded 1/2x 16-12 AWG

Tightening Torque UL/CSA: Main Circuit 10 ... 12 in·lb **Maximum Operating Voltage** Main Circuit 600 V AC UL/CSA:

# **Certificates and Declarations (Document Number)**

Data Sheet, Technical Information 1SAM300505F0108 (Part 2):

**Data Sheet, Technical Information** 

**Instructions and Manuals:** 

(Part 3):

1SAM300507F0001

1SAM300507F0003 1SAM300508F0001

1SAM300508F0003 2CDC131022M6802 1SAA963001-0101

**ABS Certificate: ATEX Certificate:** 1SAA963000-3901 **BV Certificate:** 1SAA963001-0201

**CB Certificate:** 1SAA963002-2001 **CCC Certificate:** 1SAA963001-3804 cUL Certificate: cUL\_E137861 cUL\_E345003 cULus Certificate: cUL\_E137861 Data Sheet, Technical Information: 2CDC131021D0201 **Declaration of Conformity - CE:** 1SAD938510-0125 **DNV Certificate:** 1SAA963001-0303 **EAC Certificate:** 1SAA963000-2701 **GL Certificate:** 1SAA963001-0401 **GOST Certificate:** 1SAA963001-2702 LR Certificate: 1SAA963001-0502 RINA Certificate: 1SAA963000-0802 **RMRS Certificate:** 1SAA918000-0703 **RoHS Information:** 1SAA963002-4405 **UL Certificate:** UL\_E137861 UL\_E345003

# Classifications

 E-nummer:
 3112124

 ETIM 4:
 EC000074 - Motor protective circuit-breaker

 ETIM 5:
 EC000074 - Motor protective circuit-breaker

 ETIM 6:
 EC000074 - Motor protection circuit-breaker

 eClass:
 7.0 27370401

 UNSPSC:
 39121521

 Object Classification Code:
 F

