

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (http://phoenixcontact.com/download)



Flush-type connector, Power, 4-position, SocketLink:straightLink:M12, T power, PCB mounting, SMD

#### Why buy this product

- For compact devices: transmit high power in a confined space
- ☑ Reduced mounting costs thanks to two-piece device connector
- Packaging available for automated pick and place assembly
- ✓ All common pin assignments and codings available
- 🗹 Easy device integration thanks to mechanical port screw connections with threaded attachment, press-in contour or direct integration in the front plate



#### **Key Commercial Data**

Packing unit	60 STK
Minimum order quantity	60 STK
GTIN	4 046356 989305
GTIN	4046356989305
Weight per Piece (excluding packing)	3.620 g
Custom tariff number	85366990
Country of origin	Germany
Note	Made to Order (non-returnable)

#### Technical data

#### Ambient conditions

Ambient temperature (operation)	-25 °C 105 °C (Plug / socket)
	-55 °C 105 °C (without mechanical actuation)
Degree of protection	IP67 (correctly plugged in and locked)

#### General

Note	The electrical and mechanical data specified assume that the connector
	pair is correctly locked and mounted. If the connector is unlocked and if



### Technical data

#### General

	there is a danger of contamination, the connector must be sealed using a protective cap > IP54. Influences arising from litz wires, cables or PCB assembly must also be taken into consideration.
Rated current at 40°C	12 A
Rated voltage	63 V
Rated surge voltage	1.5 kV
Number of positions	4
Insulation resistance	≥ 100 MΩ
Coding	T power
Standards/regulations	M12 connector IEC 61076-2-111 In line with
Signal type/category	Power
Overvoltage category	III
Degree of pollution	3
Connection method	SMD
Insertion/withdrawal cycles	> 100
Mounting type	PCB mounting
Type of packaging	Tray

#### Material

Flammability rating according to UL 94	V0
Contact material	CuZn
Contact surface material	Au
Contact carrier material	PA

#### Cable

Standards/specifications	M12 connector IEC 61076-2-111 In line with
--------------------------	--

#### Standards and Regulations

Standard designation	M12 connector
Standards/regulations	IEC 61076-2-111
Flammability rating according to UL 94	V0

#### **Environmental Product Compliance**

China RoHS	Environmentally Friendly Use Period = 50
	For details about hazardous substances go to tab "Downloads", Category "Manufacturer's declaration"

### **Drawings**




Schematic diagram




Pin assignment of M12 socket, 4-pos., T-coded, socket side view

Drilling diagram




Soldering pad geometry

Dimensional drawing




Dimensional drawing




M12 female connector contact carrier

View of solder side

Dimensional drawing





SMD tray packaging



### Classifications

#### eCl@ss

eCl@ss 5.1	27143423
eCl@ss 6.0	27143423
eCl@ss 8.0	27440103
eCl@ss 9.0	27440102

#### **ETIM**

ETIM 5.0	EC002061
ETIM 6.0	EC002061

#### **UNSPSC**

UNSPSC 13.2	30121413
0105-30-13.2	39121413

### Approvals

#### Approvals

Approvals

UL Listed / cUL Listed / EAC / cULus Listed

Ex Approvals

#### Approval details

UL Listed	UL	http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm		FILE E 468743
Nominal current IN			10 A	
Nominal voltage UN		-	63 V	

cUL Listed	CUL	http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm FIL		FILE E 468743
Nominal current IN			8 A	
Nominal voltage UN			63 V	

EAC	EAC	B.01742
-----	-----	---------



### Approvals

cULus Listed



#### Accessories

Accessories

Contact insert

Sample set - SACC-CI-M12FST-4P SMD-SP - 1418631



Sample set, 4-position, SocketLink:straightLink:M12, T power, PCB mounting, SMD

#### Panel mounting base

Housing screw connection - SACC-BP-F-M12/M15-6-SMD - 1414021



Housing screw connection, SocketLink:M12, Rear mounting, M15 x 1

Housing screw connection - SACC-BP-F-M12/M15-6-SMD SCO - 1414023



Housing screw connection, SocketLink:M12-SPEEDCON, Rear mounting, M15 x 1  $\,$ 

Housing screw connection - SACC-FP-F-M12/M14 SMD - 1412079



Housing screw connection, SocketLink:M12, Front mounting, M14 x 1



#### Accessories

Housing screw connection - SACC-FP-F-M12/PRESS SMD - 1412081



Housing screw connection, socket, for the two-part M12 SMD connector, for press-in mounting.

Housing screw connection - SACC-BP-F-M12/SMD-0,9/1,6-9TIP - 1419569



M12 threaded sleeve with tolerance-compensating function, for straight, SMD-solderable M12 socket contact inserts. Suitable for 0.9 mm ... 1.6 mm thick front plates.

Housing screw connection - SACC-BP-F-M12/SMD-1,6/2,3-9TIP - 1419570



M12 threaded sleeve with tolerance-compensating function, for straight, SMD-solderable M12 socket contact inserts. Suitable for 1.6 mm ... 2.3 mm thick front plates.

Housing screw connection - SACC-BP-F-M12/SMD-2,3/3,0-9TIP - 1419571



M12 threaded sleeve with tolerance-compensating function, for straight, SMD-solderable M12 socket contact inserts. Suitable for 2.3 mm ... 3.0 mm thick front plates.

Housing screw connection - SACC-BP-F-FIX/NUT-BK-SMD - 1419568



Fixing sleeve for M12 housing screw connection with tolerance-compensating function, for SMD-solderable M12 socket contact inserts.



#### Accessories

Housing screw connection - SACC-BP-F-FIX/NUT-CY-SMD - 1419565



Fixing sleeve for M12 housing screw connection with tolerance-compensating function, for SMD-solderable M12 socket contact inserts.

Housing screw connection - SACC-BP-F-FIX/NUT-GN-SMD - 1419566



Fixing sleeve for M12 housing screw connection with tolerance-compensating function, for SMD-solderable M12 socket contact inserts.

Housing screw connection - SACC-BP-F-FIX/NUT-VT-SMD - 1419567



Fixing sleeve for M12 housing screw connection with tolerance-compensating function, for SMD-solderable M12 socket contact inserts.

Phoenix Contact 2016 @ - all rights reserved http://www.phoenixcontact.com