

## RA-4961-K1Q Wireless Receiver and Wireless Pushbutton

The RA-4961-K1Q Wireless Alert System can be synced with a wide variety of wireless devices to suit almost any situation.

### Kit Includes:

- Wireless Receiver (RA-4961Q)
- Wireless Pushbutton (RA-4961-PBQ)

### Features:

- Up to 1,000ft (305m) transmission range\*
- Uses 914.8 MHz Frequency for less interference
- Audible (volume adjustable) and visual alert via built-in speaker and flashing light
- 18 programmable ringtones for each accessory
- Connect up to 4 wireless transmitter accessories
- Each channel independently programmable
- Output terminals for optional auxiliary device
- Low battery LED indicators on receiver unit for receiver and connected sensors
- Wall or desktop mountable



### Optional Accessories:

- Wireless Outdoor PIR Sensor (RA-4961-DSQ)
- Wireless Indoor PIR Sensor (RA-4961-PRQ)
- Wireless Mailbox/Tilt Sensor (RA-4961-MBQ)
- Wireless Magnetic Contact (RA-4961-MCQ)
- Wireless Vibrating Receiver (RA-4961-VPQ)

### Specifications:

Model	RA-4961Q Receiver
Frequency	914.8MHz
Channels	4
Accessories per channel	1
Relay output (Channel 4 only)	1(Form C Relay), 1A@50VDC
Power Supply	3 "C" batteries (not included) or 6VDC power adapter (X-HKP06-06005 - not included)
Estimated battery life	270 days (3 triggers/day)
Low battery indicator	Notification LED flashes every 5 seconds
Accessory low battery indicator	Zone LED for accessory blinks continuously
Sound level (dB)	Up to 96dB@1ft(30cm)
Operating temperature	32°~140°F (0°~60°C)
Dimensions	5 1/4" x 1 9/16" x 6 5/8" (133x40x169mm)

Model	RA-4961-PBQ Pushbutton
Frequency	914.8MHz
Transmission range*	Up to 1,000ft (305m)
Channels	1
Power supply	CR2032 Battery (included)
Estimated battery life	400 days (3 triggers/day)
Low battery indicator	Zone LED on receiver blinks continuously
IP rating	IP45
Operating temperature	-4°~140°F (-20°~60°C)
Dimensions	1 5/16" x 1 1/16" x 3 7/16" (34x18x87mm)

\*Line of sight. Transmission range will vary depending on installation and operating environment.

### SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: [www.seco-larm.com](http://www.seco-larm.com) Email: [sales@seco-larm.com](mailto:sales@seco-larm.com)