

TECHNICAL DATA SHEET

PRO-ELEC

Hook and Loop Braided Wrap CB19669-CB19672

**RoHS
Compliant**

Specification	
Material	Polyester
Hook and Loop	Polyamide
Operating range	-50°C~150°C
Melting point	240±10°C
Standard colour	Black, white, grey
Certification	RoHS
Flammability	VW-1
Cutting tool	Hot knife

Conditions of use

1. Hook and loop braided wrap can help to create a tidy and well-regulated environment. It can be easily wrapped and closed over the cables. It can be re-opened rapidly to manage cables to be added or removed, and breakouts can be made simply by feeding cables out. Open weave design easily conforms to many irregular shapes.
2. Hook and Loop Braided Wrap is widely used for management of A/V cables and power cord in home theater, computer, TV support etc.

Nominal Size (mm)	Hook & Loop Width (mm)	Max bundle dia (mm)	Packing (m/spool)
13	10	8	25m
19	10	12	25m
32	20	20	25m
51	20	32	25m
64	20	40	25m



Description	Code
Hook and Loop Braided Wrap 19mm Black 2m	BVCW019-2M
Hook and Loop Braided Wrap 32mm Black 2m	BVCW032-2M
Hook and Loop Braided Wrap 19mm Black 1m	BVCW019-1M
Hook and Loop Braided Wrap 32mm Black 1m	BVCW032-1M

Important Notice : This data sheet and its contents (the "Information") belong to pro-ELEC. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but pro-ELEC assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where pro-ELEC was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict pro-ELEC's liability for death or personal injury resulting from its negligence.

PRO-ELEC