SMA R/A PCB Mount Jack Receptacle





Specifications

Connector Body Style : Right Angle Jack Receptacle

Coaxial Termination : Through Hole Connector Mounting : PCB Mount

RoHS Compliant

Electrical Specifications

Frequency Range : DC – 12.4GHz

 $\begin{array}{lll} \mbox{Nominal Impedance} & : 50\Omega \\ \mbox{Voltage Rating} & : 500\mbox{V Max.} \\ \mbox{VSWR} & : 1.23\mbox{ Max} \end{array}$

Material Specifications

Bodies : Brass per JIS-C3604 Centre Contact : Brass per JIS-C3604

Beryllium Copper per ASTM B196 UNS C17300

Insulation : PTFE per ASTM D1457 and ASTM D1710


Mechanical Specifications


Interface in accordance with : MIL-STD-348A


Environmental Specifications

Operating Temperature : -65°C to +165°C

Diagram







Dimensions: Millimetres (Inches)

www.element14.com www.farnell.com www.newark.com



SMA R/A PCB Mount Jack Receptacle



No.	Description	Material	Finish
1	Chassis	Brass	Gold 3µ" Min.
2	Insulation	PTFE	-
3	Centre Contact I	Beryllium Copper	Gold 50µ" Min.
4	Body	Brass	Gold 3µ" Min.
5	Insulation	PTFE	-
6	Centre Contact II	Beryllium Copper	Gold 50µ" Min.
7	Сар	Brass	Gold 3µ" Min.

Part Number Table

Description	Part Number
SMA R/A PCB Mount Jack Receptacle, Through Hole, 50Ω	19-49-5-TGG

Important Notice: This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell Limited 2016.

www.element14.com www.farnell.com www.newark.com

