

# FILTLTE

## MASTHEAD FILTERS



FILTLTE 1 In 1 Out Masthead 782MHz Filter Technical Specification.

SPECIFICATION	
Working Frequency	5-782MHz
Connectors	1 In 1 Out (All F female connector)
Insertion Loss 5-778MHz	$\leq 1\text{dB}$
Insertion Loss 780-784MHz	$\leq 6\text{dB}$
Rejection 758-862MHz	$\geq 20\text{dB}$
DC PASS	Not required

