

Smart Digital Multimeter **multicomp**PRO

Description

MP730835 smart digital multimeter is designed to automatically identify AC/DC voltage, resistance, diode, and continuity. With the press of one button, all measurement modes can be manually selected including capacitance. The compact design and EBTN display makes it a great tool for home, DIY, and working in dark environments.

**RoHS
Compliant**



Features

- True RMS
- NCV/Live
- Low Battery Indication: $\leq 2.7V$
- Data Hold
- Auto Power Off
- Acousto-optic indication: NCV/continuity/battery power

Specifications

Category ratings	: CAT III 600V
DC voltage (V)	: 600V $\pm(0.5\%+3)$
AC voltage (V)	: 600V $\pm(0.8\%+3)$
DC Current (A)	: 10A $\pm(1\%+3)$
AC Current (A)	: 10A $\pm(1.2\%+3)$
Resistance (Ω)	: 40M Ω $\pm(0.8\%+2)$
Capacitance (F)	: 4000 μ F $\pm(4\%+5)$

General Characteristics

Power	: 1.5V battery (R03) \times 2
Display	: 44mm \times 26mm
Product net weight	: 130g
Product size	: 130mm \times 65mm \times 28mm
Standard accessories	: English manual
Standard individual packing	: Gift box
Standard quantity per carton	: 60pcs
Standard carton measurement	: 480mm \times 340mm \times 325mm
Standard carton gross weight	: 16.1kg

Part Number Table

Description	Part Number
Hand Held Smart Digital Multimeter, 0.6V AC/DC to 600V AC/DC	MP730835

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro
Farnell.com/multicomp-pro
Element14.com/multicomp-pro

multicompPRO