



## P604BB/BG/BS/BW 6w 100V Line Ceiling Speaker

### User Instructions

### IMPORTANT

#### Installer and Users please note:

These instructions should be read carefully and left with the user of the product for future reference. These speakers should only be installed by competent trained installers and are not designed for domestic use.

#### BEFORE USE

Inspect the product including its cable and contacts for any signs of damage. If the product is damaged, DO NOT use it, and contact your supplier immediately

#### INSTALLATION INSTRUCTIONS

This speaker is only intended for use on a 100V line speaker system and should not be installed on any other system.

The speaker is rated at 2, 4 and 6W, it is the installer's responsibility to ensure that the amplifier is sufficiently rated to drive the number of speakers in the system.

The Speaker Terminal Block outputs are as follows;

Black - Common

Red - 6W

Yellow - 4W

Green - 2W

All speakers should be wired from the Common and 100V terminals on the amplifier to the Black (common) and one other required connection on the speaker. The unit is designed to be ceiling mounted using the built in spring clips. To ceiling mount drill a hole 85mm in diameter in the required position. Wire the connections into the correct terminals. The spring clips should be folded up and back towards the speaker to fit through the hole and release the clips to hold in place. The relevant wattage settings act like volume controls for the speaker output. The higher the wattage the higher the volume of the speaker.

#### Specifications

Dimensions .....105 x 105 x 79 mm  
Cut Out Diameter ..... 85mm  
Max Ceiling Depth..... 25mm  
Mounting Depth..... 74mm  
Tappings ..... 2, 4, 6W  
Weight.....500g  
Frequency Response .....150 - 16000Hz  
Sensitivity..... 90dBV/Pa

#### SERVICE WARRANTY

Eagle guarantees the product free from defects in materials and workmanship for a period of twelve months.

Should this item be installed or used under conditions other than those recommended, at voltages other than the voltage indicated on the appliance, or any attempts made to service or modify the unit, then the warranty will be rendered void.

The product you buy may sometimes differ slightly from illustrations. This warranty is in addition to, and does not affect, your statutory rights.

Our guarantee is administered by our retailers.

If your product arrives damaged, you must contact the retailer from whom you bought it. The retailer's contact details will be on the invoice that arrived with the product, or on the e-mail you received when you placed the order. Do not contact Eagle, only your retailer can arrange a replacement.

If your product fails within the guarantee period. If the product needs to be repaired or replaced, you must contact the retailer from whom you bought it.

The retailer's contact details will be on the invoice that arrived with the product, or on the e-mail you received when you placed the order.

If you have just received your product and require technical help in using it, please call our Help Desk on (0845) 459 4816

If you have any other technical queries about the product, please call our Help Desk on (0845) 459 4816.

Electrovision Ltd.,  
Lancots Lane, Sutton,  
St. Helens, Merseyside.  
WA9 3EX  
[www.electrovision.co.uk](http://www.electrovision.co.uk)