SIEMENS

Data sheet 3UG4622-1AW30



Digital monitoring relay Current monitoring, 22.5 mm from 0.05-10 A AC/DC Overshoot and undershoot 24 to 240 V AC/DC 50 to 60 Hz DC and AC ON delay and noise pulses delay 0.1 to 20 s Hysteresis 0.01 to 5 A 1 change-over contact with or without fault buffer screw terminal Successor product for 3UG3522-1AL20, 3UG3522-1AG20 and 3UG3522-1AC48-0AA1

product brand name	SIRIUS
product designation	Current monitoring relay with digital setting
product type designation	3UG4
General technical data	
product function	Current monitoring relay
design of the display	LCD
insulation voltage for overvoltage category III according to IEC 60664	
 with degree of pollution 3 rated value 	690 V
degree of pollution	3
surge voltage resistance rated value	4 kV
maximum permissible voltage for safe isolation	
 between auxiliary and auxiliary circuit 	300 V
between control and auxiliary circuit	300 V
protection class IP	IP20
shock resistance acc. to IEC 60068-2-27	sinusoidal half-wave 15g / 11 ms
vibration resistance acc. to IEC 60068-2-6	1 6 Hz: 15 mm, 6 500 Hz: 2g
mechanical service life (switching cycles) typical	10 000 000
electrical endurance (switching cycles) at AC-15 at 230 V typical	100 000
thermal current of the switching element with contacts maximum	5 A
reference code acc. to IEC 81346-2	K
relative repeat accuracy	1 %
Substance Prohibitance (Date)	01.05.2012
Product Function	
product function	
 overcurrent detection 1 phase 	Yes
 overcurrent detection 3 phase 	No
 undercurrent detection 1 phase 	Yes
 undercurrent detection 3 phases 	No
 overcurrent detection DC 	Yes
 undercurrent detection DC 	Yes
 current window recognition DC 	Yes
 voltage window recognition 1 phase 	No
 voltage window recognition 3 phase 	No
 adjustable open/closed-circuit current principle 	Yes
 external reset 	Yes
• auto-RESET	Yes
Supply voltage	

turns of voltage of the cumply voltage	ACIDO			
type of voltage of the supply voltage	AC/DC			
supply voltage 1 at AC • at 50 Hz	20.4 264.7			
• at 60 Hz	20.4 264 V 20.4 264 V			
supply voltage 1 at DC	20.4 264 V			
Measuring circuit	20.4 204 V			
	AC/DC			
type of current for monitoring measurable current				
	0.05 15 A			
measurable line frequency	40 500 Hz			
adjustable current response value current • 1	0.05 10.4			
• 2	0.05 10 A 0.05 10 A			
adjustable response delay time	0.05 10 A			
when starting	0.1 20 s			
with lower or upper limit violation	0.1 20 s			
adjustable switching hysteresis for measured current	10 5 000 mA			
value	10 0 000 HIA			
buffering time in the event of power failure minimum	10 ms			
accuracy of digital display	+/-1 digit			
relative temperature-related measurement deviation	5 %			
internal resistance of the measuring circuit	5 mΩ			
Precision				
relative metering precision	5 %			
temperature drift per °C	0.1 %/°C			
Auxiliary circuit				
number of NC contacts delayed switching	0			
number of NO contacts delayed switching	0			
number of CO contacts delayed switching	1			
operating frequency with 3RT2 contactor maximum	5 000 1/h			
Main circuit				
Main circuit number of poles for main current circuit	1			
	1 24 240 V			
number of poles for main current circuit				
number of poles for main current circuit operating voltage rated value				
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz	24 240 V			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13	24 240 V 3 A			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz	24 240 V 3 A 3 A			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V	24 240 V 3 A 3 A 1 A 0.2 A			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V operational current at 17 V minimum	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A 0.005 A			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V operational current at 17 V minimum continuous current of the DIAZED fuse link of the	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V operational current at 17 V minimum continuous current of the DIAZED fuse link of the output relay	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A 0.005 A			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V operational current at 17 V minimum continuous current of the DIAZED fuse link of the output relay Electromagnetic compatibility	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A 0.005 A			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V operational current at 17 V minimum continuous current of the DIAZED fuse link of the output relay Electromagnetic compatibility conducted interference	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A 0.005 A			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V operational current at 17 V minimum continuous current of the DIAZED fuse link of the output relay Electromagnetic compatibility conducted interference • due to burst acc. to IEC 61000-4-4	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A 0.005 A 4 A			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V operational current at 17 V minimum continuous current of the DIAZED fuse link of the output relay Electromagnetic compatibility conducted interference • due to burst acc. to IEC 61000-4-4 • due to conductor-earth surge acc. to IEC 61000-4-5	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A 0.005 A 4 A			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V operational current at 17 V minimum continuous current of the DIAZED fuse link of the output relay Electromagnetic compatibility conducted interference • due to burst acc. to IEC 61000-4-4	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A 0.005 A 4 A			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V operational current at 17 V minimum continuous current of the DIAZED fuse link of the output relay Electromagnetic compatibility conducted interference • due to burst acc. to IEC 61000-4-4 • due to conductor-earth surge acc. to IEC 61000-4-5 • due to conductor-conductor surge acc. to IEC 61000-4-5 field-based interference acc. to IEC 61000-4-3	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A 0.005 A 4 A 2 kV 2 kV 1 kV			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V operational current at 17 V minimum continuous current of the DIAZED fuse link of the output relay Electromagnetic compatibility conducted interference • due to burst acc. to IEC 61000-4-4 • due to conductor-earth surge acc. to IEC 61000-4-5 • due to conductor-conductor surge acc. to IEC 61000-4-5 field-based interference acc. to IEC 61000-4-3 electrostatic discharge acc. to IEC 61000-4-2	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A 0.005 A 4 A 2 kV 2 kV 1 kV			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V operational current at 17 V minimum continuous current of the DIAZED fuse link of the output relay Electromagnetic compatibility conducted interference • due to burst acc. to IEC 61000-4-4 • due to conductor-earth surge acc. to IEC 61000-4-5 • due to conductor-conductor surge acc. to IEC 61000-4-5 field-based interference acc. to IEC 61000-4-3	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A 0.005 A 4 A 2 kV 2 kV 1 kV			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V operational current at 17 V minimum continuous current of the DIAZED fuse link of the output relay Electromagnetic compatibility conducted interference • due to burst acc. to IEC 61000-4-4 • due to conductor-earth surge acc. to IEC 61000-4-5 • due to conductor-conductor surge acc. to IEC 61000-4-5 field-based interference acc. to IEC 61000-4-3 electrostatic discharge acc. to IEC 61000-4-2 Galvanic isolation design of the electrical isolation	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A 0.005 A 4 A 2 kV 2 kV 1 kV			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V operational current at 17 V minimum continuous current of the DIAZED fuse link of the output relay Electromagnetic compatibility conducted interference • due to burst acc. to IEC 61000-4-4 • due to conductor-earth surge acc. to IEC 61000-4-5 • due to conductor-conductor surge acc. to IEC 61000-4-5 field-based interference acc. to IEC 61000-4-3 electrostatic discharge acc. to IEC 61000-4-2 Galvanic isolation design of the electrical isolation galvanic isolation	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A 0.005 A 4 A 2 kV 2 kV 1 kV 10 V/m 6 kV contact discharge / 8 kV air discharge			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V operational current at 17 V minimum continuous current of the DIAZED fuse link of the output relay Electromagnetic compatibility conducted interference • due to burst acc. to IEC 61000-4-4 • due to conductor-earth surge acc. to IEC 61000-4-5 • due to conductor-conductor surge acc. to IEC 61000-4-5 field-based interference acc. to IEC 61000-4-3 electrostatic discharge acc. to IEC 61000-4-2 Galvanic isolation design of the electrical isolation galvanic isolation • between input and output	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A 0.005 A 4 A 2 kV 2 kV 1 kV 10 V/m 6 kV contact discharge / 8 kV air discharge			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V operational current at 17 V minimum continuous current of the DIAZED fuse link of the output relay Electromagnetic compatibility conducted interference • due to burst acc. to IEC 61000-4-4 • due to conductor-earth surge acc. to IEC 61000-4-5 • due to conductor-conductor surge acc. to IEC 61000-4-5 field-based interference acc. to IEC 61000-4-3 electrostatic discharge acc. to IEC 61000-4-2 Galvanic isolation design of the electrical isolation galvanic isolation • between input and output • between the outputs	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A 0.005 A 4 A 2 kV 2 kV 1 kV 10 V/m 6 kV contact discharge / 8 kV air discharge			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V operational current at 17 V minimum continuous current of the DIAZED fuse link of the output relay Electromagnetic compatibility conducted interference • due to burst acc. to IEC 61000-4-4 • due to conductor-earth surge acc. to IEC 61000-4-5 • due to conductor-conductor surge acc. to IEC 61000-4-5 field-based interference acc. to IEC 61000-4-3 electrostatic discharge acc. to IEC 61000-4-2 Galvanic isolation design of the electrical isolation galvanic isolation • between input and output • between the outputs • between the voltage supply and other circuits	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A 0.005 A 4 A 2 kV 2 kV 1 kV 10 V/m 6 kV contact discharge / 8 kV air discharge			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V operational current at 17 V minimum continuous current of the DIAZED fuse link of the output relay Electromagnetic compatibility conducted interference • due to burst acc. to IEC 61000-4-4 • due to conductor-earth surge acc. to IEC 61000-4-5 • due to conductor-conductor surge acc. to IEC 61000-4-5 field-based interference acc. to IEC 61000-4-3 electrostatic discharge acc. to IEC 61000-4-2 Galvanic isolation design of the electrical isolation galvanic isolation • between input and output • between the outputs	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A 0.005 A 4 A 2 kV 2 kV 1 kV 10 V/m 6 kV contact discharge / 8 kV air discharge Protective separation Yes Yes			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V operational current at 17 V minimum continuous current of the DIAZED fuse link of the output relay Electromagnetic compatibility conducted interference • due to burst acc. to IEC 61000-4-4 • due to conductor-earth surge acc. to IEC 61000-4-5 • due to conductor-conductor surge acc. to IEC 61000-4-5 field-based interference acc. to IEC 61000-4-3 electrostatic discharge acc. to IEC 61000-4-2 Galvanic isolation design of the electrical isolation galvanic isolation • between input and output • between the outputs • between the voltage supply and other circuits Connections/ Terminals product component removable terminal for main	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A 0.005 A 4 A 2 kV 2 kV 1 kV 10 V/m 6 kV contact discharge / 8 kV air discharge			
number of poles for main current circuit operating voltage rated value ampacity of the output relay at AC-15 • at 250 V at 50/60 Hz • at 400 V at 50/60 Hz ampacity of the output relay at DC-13 • at 24 V • at 125 V • at 250 V operational current at 17 V minimum continuous current of the DIAZED fuse link of the output relay Electromagnetic compatibility conducted interference • due to burst acc. to IEC 61000-4-4 • due to conductor-earth surge acc. to IEC 61000-4-5 • due to conductor-conductor surge acc. to IEC 61000-4-5 field-based interference acc. to IEC 61000-4-3 electrostatic discharge acc. to IEC 61000-4-2 Galvanic isolation design of the electrical isolation galvanic isolation • between input and output • between the outputs • between the voltage supply and other circuits Connections/ Terminals	24 240 V 3 A 3 A 1 A 0.2 A 0.1 A 0.005 A 4 A 2 kV 2 kV 1 kV 10 V/m 6 kV contact discharge / 8 kV air discharge Protective separation Yes Yes Yes			

and control circuit				
type of electrical connection				
for main current circuit	screw-type terminals			
for auxiliary and control circuit	screw-type terminals			
type of connectable conductor cross-sections				
• solid	1x (0.5 4.0 mm²), 2x (0.5 2.5 mm²)			
 finely stranded with core end processing 	1x (0.5 2.5 mm²), 2x (0.5 1.5 mm²)			
 at AWG cables solid 	2x (20 14)			
 at AWG cables stranded 	2x (20 14)			
connectable conductor cross-section				
• solid	0.5 4 mm²			
 finely stranded with core end processing 	0.5 2.5 mm²			
AWG number as coded connectable conductor cross section				
• solid	20 14			
stranded	20 14			
tightening torque with screw-type terminals	0.8 1.2 N·m			
stallation/ mounting/ dimensions				
mounting position	any			
fastening method	snap-on mounting			
height	92 mm			
width	22.5 mm			
depth	91 mm			
required spacing				
with side-by-side mounting				
— forwards	0 mm			
— backwards	0 mm			
— upwards	0 mm			
— downwards	0 mm			
— at the side	0 mm			
for grounded parts				
— forwards	0 mm			
— backwards	0 mm			
— upwards	0 mm			
— at the side	0 mm			
— downwards	0 mm			
for live parts				
— forwards	0 mm			
— backwards	0 mm			
— upwards	0 mm			
— downwards	0 mm			
— at the side	0 mm			
mbient conditions				
installation altitude at height above sea level maximum	2 000 m			
ambient temperature				
during operation	-25 +60 °C			
during storage	-40 +85 °C			
during transport	-40 +85 °C			
Sertificates/ approvals				
	Declaration of			
General Product Approval	EMC Declaration of Conformity Test Certificate			
@ !	Type Test Certificates/Test Report			











Test Certificates	Marine / Shipping	other	Railway
-------------------	-------------------	-------	---------

Special Test Certificate





Confirmation Vibration and Shock

Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3UG4622-1AW30

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3UG4622-1AW30

 ${\bf Service \& Support\ (Manuals,\ Certificates,\ Characteristics,\ FAQs,...)}$

https://support.industry.siemens.com/cs/ww/en/ps/3UG4622-1AW30

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3UG4622-1AW30&lang=en

Characteristic: Derating

https://support.industry.siemens.com/cs/ww/en/ps/3UG4622-1AW30/manual

7