


3-Way Crossover Network




Description:

3-Way Crossover is designed for use as a replacement crossover, or for a new speaker building project, this low cost crossover is ideal for use in medium-sized 3-way speakers.



Features:

- 12dB per Octave
- Power Handling: 60W RMS
- Crossover frequencies: 700Hz and 3KHz
- Designed for 8Ω drivers
- Dimensions: 4 (H) x 2½" (W) x 1" (D)

PCB Layout



Schematics Diagram



Part Number Table

Description	Part Number
3-Way Crossover Network - 12dB/Octave 700Hz/3KHz 60W RMS	50-786

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

