Extension Leads





Specifications

No. of Outlets : 2 Outlets
Outlet Type : UK
Current Rating : 13A
Supply Voltage : 250V AC
Plug Type : UK

Construction

Socket Base and Cover : FRPP Socket Terminals (Bus bar) : Brass

Cover Screw : Mild Steel Nickel Plated

Shutter : Nylon (PA)
Spring : Mild Steel
Neon Lamp with 220kΩ Resistor
Neon Lamp Cover : Polycarbonate (PC)
Surge Component : Metal Oxide Varistor
Pluq : 13A, BS 1363 pluq

Cable : PVC, EN50525-2-11 3X1.25mm²

Standard

BS 1363/A, BS 5733

Part Number Table

	Description	Part Number
ı	Extension Lead, 2 Outlets, 13A, UK Type, 2m	1202NS-2M

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. pro-ELEC is the registered trademark of Premier Farnell Limited 2019.

Newark.com/exclusive-brands Farnell.com/exclusive-brands Element14.com/exclusive-brands

