

Part Number: R-3W2-KB

Voltage Indicator with Flashing LED's, Multi-Environment (Cat III/Cat IV) with Bezel Mount





<https://shop.graceport.com/products/r-3w2-kb>






Product Specifications

| Component Details | |
|-------------------------------|---|
| Part Number | R-3W2-KB |
| Includes | Mult-Environment Voltage Indicator and Bezel Mount |
| Electrical Specifications | |
| Voltage Indicator (R-3W2) | Flashing LEDs, Multi-Environment (Cat III/Cat IV Rated) |
| Voltage Type | AC/DC |
| Operational Voltage Range | 40-600VAC 50/60Hz, 30-1000VDC |
| Storage Temperature Range | -45°C to + 85°C |
| Operational Temperature Range | -20°C to +55°C |
| Voltage to Door Required | No |
| Lead Connections | 3 Phase, 4 Wire |
| Mechanical Specifications | |
| Installation | 30mm Pushbutton Hole |
| Mounting Location | External (Door/Flange Bezel Mounted) |
| Commercial Data | |
| Country of Origin | Taiwan |
| Schedule B Code | 8531.80.9051 |

Approval Certifications

| Logo | Approval | Additional Text | Certificate Name | |
|--|---|-----------------|------------------|---|
|  | UL Underwriters Laboratories Inc. | | E334957 |  |
|  | CE European Conformity | INGR0516-A-00 | SS0003-0616-C-CE |  |

Datasheets

| Name | |
|---|--|
| Voltage Indicator Datasheet |  |
| Voltage Indicator Datasheet Spanish |  |
| Voltage Indicator Class 1, Div 2 Installation Guide |  |

Don't see what you're looking for?

Contact us at sales@gracetechnologies.com, call 1-800-280-9517 or visit www.graceport.com to chat with our customer service.