

HAY-FIRE-DO

Fire Indicator Detector Operated

- Operating Voltage: 3VDC or 24VDC
- Nominal Current Consumption: 5mA
- Enclosure Material: Plastic
- Fits standard single gang plastic gang box: not supplied
- Dimensions: W.86 x L.86 x H.15mm
- Weight: 0.1kg
- Warranty: 3 years



HAY-FIRE-24R

Fire 24V Relay

- Operating Voltage: 24VDC $\pm$ 10%
- Nominal Current Consumption: 22mA
- Relay: Double Pole
- Relay Coil Impedance: 1067 Ohms
- Enclosure Material: Plastic
- Dimensions: W.86 x L.86 x H.62mm (faceplate)
- Surface Back Box Supplied
- Weight: 0.2kg
- Warranty: 3 years

