

Power Inductor-Wirewound

Automotive



AWV200PWR-KIT JIS 2016 Size

Designer Kit Contents

Pulse - Std Power Part Number	L (mm)	W(mm)	T (mm)	SIZE Code (JIS)	Inductance (nH)	Tolerance (±%)	RDC(Ω) Max.	IDC(mA)Max.	Quantity
AWVC00201610R24M00	2.0	1.6	1.0	2016	0.24	20	0.026	2.7	20
AWVC00201610R24T00	2.0	1.6	1.0	2016	0.24	30	0.026	2.7	20
AWVH00201610R24MH1	2.0	1.6	1.0	2016	0.24	20	0.048	2.1	20
AWVH00201610R24TH1	2.0	1.6	1.0	2016	0.24	30	0.048	2.1	20
AWVH00201610R33MH1	2.0	1.6	1.0	2016	0.33	20	0.048	2.1	20
AWVH00201610R33TH1	2.0	1.6	1.0	2016	0.33	30	0.048	2.1	20
AWVH00201610R47MH1	2.0	1.6	1.0	2016	0.47	20	0.072	1.8	20
AWVH00201610R47TH1	2.0	1.6	1.0	2016	0.47	30	0.072	1.8	20
AWVT00201610R47M00	2.0	1.6	1.0	2016	0.47	20	0.072	2.1	20
AWVT00201610R47T00	2.0	1.6	1.0	2016	0.47	30	0.072	2.1	20
AWVF00201612R47M00	2.0	1.6	1.2	2016	0.47	20	0.051	2	20
AWVF00201612R47T00	2.0	1.6	1.2	2016	0.47	30	0.051	2	20
AWVC00201612R50M00	2.0	1.6	1.2	2016	0.5	20	0.051	2	20
AWVC00201612R50T00	2.0	1.6	1.2	2016	0.5	30	0.051	2	20
AWVH00201610R56MH1	2.0	1.6	1.0	2016	0.56	20	0.072	1.8	20
AWVH00201610R56TH1	2.0	1.6	1.0	2016	0.56	30	0.072	1.8	20
AWVH00201610R68MH1	2.0	1.6	1.0	2016	0.68	20	0.092	1.5	20
AWVH00201610R68TH1	2.0	1.6	1.0	2016	0.68	30	0.092	1.5	20
AWVF00201612R68M00	2.0	1.6	1.2	2016	0.68	20	0.074	1.8	20
AWVF00201612R68T00	2.0	1.6	1.2	2016	0.68	30	0.074	1.8	20
AWVC002016101R0M00	2.0	1.6	1.0	2016	1	20	0.095	1.6	20
AWVC002016101R0T00	2.0	1.6	1.0	2016	1	30	0.095	1.6	20
AWVH002016101R0MH1	2.0	1.6	1.0	2016	1	20	0.11	1.2	20
AWVH002016101R0TH1	2.0	1.6	1.0	2016	1	30	0.11	1.2	20
AWVC002016121R0M00	2.0	1.6	1.2	2016	1	20	0.083	1.6	20
AWVC002016121R0T00	2.0	1.6	1.2	2016	1	30	0.083	1.6	20
AWVC002016101R5M00	2.0	1.6	1.0	2016	1.5	20	0.14	1.4	20
AWVC002016101R5T00	2.0	1.6	1.0	2016	1.5	30	0.14	1.4	20
AWVF002016121R5M00	2.0	1.6	1.2	2016	1.5	20	0.13	1.3	20
AWVF002016121R5T00	2.0	1.6	1.2	2016	1.5	30	0.13	1.3	20
AWVC002016102R2M00	2.0	1.6	1.0	2016	2.2	20	0.19	1.1	20
AWVC002016102R2T00	2.0	1.6	1.0	2016	2.2	30	0.19	1.1	20
AWVH002016102R2MH1	2.0	1.6	1.0	2016	2.2	20	0.205	0.97	20
AWVH002016102R2TH1	2.0	1.6	1.0	2016	2.2	30	0.205	0.97	20
AWVC002016122R2M00	2.0	1.6	1.2	2016	2.2	20	0.159	1.2	20
AWVC002016122R2T00	2.0	1.6	1.2	2016	2.2	30	0.159	1.2	20
AWVC002016103R3M00	2.0	1.6	1.0	2016	3.3	20	0.295	0.88	20
AWVC002016103R3T00	2.0	1.6	1.0	2016	3.3	30	0.295	0.88	20
AWVH002016103R3MH1	2.0	1.6	1.0	2016	3.3	20	0.38	0.8	20
AWVH002016103R3TH1	2.0	1.6	1.0	2016	3.3	30	0.38	0.8	20
AWVC002016123R3M00	2.0	1.6	1.2	2016	3.3	20	0.22	0.95	20
AWVC002016123R3T00	2.0	1.6	1.2	2016	3.3	30	0.22	0.95	20
AWVC002016104R7M00	2.0	1.6	1.0	2016	4.7	20	0.36	0.81	20
AWVC002016104R7T00	2.0	1.6	1.0	2016	4.7	30	0.36	0.81	20
AWVH002016104R7MH1	2.0	1.6	1.0	2016	4.7	20	0.52	0.68	20
AWVH002016104R7TH1	2.0	1.6	1.0	2016	4.7	30	0.52	0.68	20
AWVC002016124R7M00	2.0	1.6	1.2	2016	4.7	20	0.33	0.81	20
AWVC002016124R7T00	2.0	1.6	1.2	2016	4.7	30	0.33	0.81	20
AWVC002016106R8M00	2.0	1.6	1.0	2016	6.8	20	0.64	0.63	20
AWVC002016106R8T00	2.0	1.6	1.0	2016	6.8	30	0.64	0.63	20

Power Inductor-Wirewound

Automotive



AWV200PWR-KIT JIS 2016 Size

Designer Kit Contents

Pulse - Std Power Part Number	L (mm)	W(mm)	T (mm)	SIZE Code (JIS)	Inductance (nH)	Tolerance (±%)	RDC(Ω) Max.	IDC(mA)Max.	Quantity
AWVF002016126R8M00	2.0	1.6	1.2	2016	6.8	20	0.465	0.7	20
AWVF002016126R8T00	2.0	1.6	1.2	2016	6.8	30	0.465	0.7	20
AWVC00201610100M00	2.0	1.6	1.0	2016	10	20	1	0.5	20
AWVC00201610100T00	2.0	1.6	1.0	2016	10	30	1	0.5	20
AWVH00201610100MH1	2.0	1.6	1.0	2016	10	20	1.1	0.38	20
AWVH00201610100TH1	2.0	1.6	1.0	2016	10	30	1.1	0.38	20
AWVC00201612100M00	2.0	1.6	1.2	2016	10	20	0.58	0.52	20
AWVC00201612100T00	2.0	1.6	1.2	2016	10	30	0.58	0.52	20
AWVC00201610150M00	2.0	1.6	1.0	2016	15	20	1.5	0.37	20
AWVC00201610150T00	2.0	1.6	1.0	2016	15	30	1.5	0.37	20
AWVC00201612150M00	2.0	1.6	1.2	2016	15	20	0.9	0.4	20
AWVC00201612150T00	2.0	1.6	1.2	2016	15	30	0.9	0.4	20
AWVC00201610180M00	2.0	1.6	1.0	2016	18	20	1.6	0.36	20
AWVC00201610180T00	2.0	1.6	1.0	2016	18	30	1.6	0.36	20
AWVC00201610220M00	2.0	1.6	1.0	2016	22	20	1.7	0.36	20
AWVC00201610220T00	2.0	1.6	1.0	2016	22	30	1.7	0.36	20
AWVC00201612220M00	2.0	1.6	1.2	2016	22	20	1.4	0.36	20
AWVC00201612220T00	2.0	1.6	1.2	2016	22	30	1.4	0.36	20

Power Inductor-Wirewound

Automotive



AWV200PWR-KIT JIS 2016 Size

Dimensions – Millimeters (Inches)

