

Power Inductor-Multilayer



BKP160PWR-KIT JIS 1608, 2520 Size

Designer Kit Contents

Pulse - Std Power Part Number	L (mm)	W (mm)	T (mm)	Inductance (μ H)	Tolerance ($\pm$ %)	RDC(Ω) Max.	Isat(A)	Irms(A)	Quantity
BKPB001608DZR47MA2	1.6	0.8	0.8	0.47	20	0.15	0.4	1.1	20
BKPB001608DZR47TA2	1.6	0.8	0.8	0.47	30	0.15	0.4	1.1	20
BKPB001608DZ1R0MA2	1.6	0.8	0.8	1	20	0.2	0.2	0.95	20
BKPB001608DZ1R0TA2	1.6	0.8	0.8	1	30	0.2	0.2	0.95	20
BKPE001608DZ1R0MA6	1.6	0.8	0.8	1	20	0.13	0.5	1.3	20
BKPE001608DZ1R0TA6	1.6	0.8	0.8	1	30	0.13	0.5	1.3	20
BKPB001608DZ2R2MA2	1.6	0.8	0.8	2.2	20	0.3	0.15	0.75	20
BKPB001608DZ2R2TA2	1.6	0.8	0.8	2.2	30	0.3	0.15	0.75	20
BKPE001608DZ2R2MA6	1.6	0.8	0.8	2.2	20	0.38	0.3	0.7	20
BKPE001608DZ2R2TA6	1.6	0.8	0.8	2.2	30	0.38	0.3	0.7	20
BKPA002520102R2M00	2.5	2.0	1.0	2.2	20	0.15	0	1	20

BKP160PWR-KIT JIS 1608, 2520 Size

Dimensions – Millimeters (Inches)

