


The HDMI to SDI Converter allows HDMI signals to be shown on two SDI displays while ensuring high bit rates of 12 Gbit/s to give you high resolution signal without any loss. For professionals this means that it is now easier to convert your high def HDMI signal with audio to SDI for long distance transmission and display your work on two SDI displays. Also, a 2 CH L/R audio input allows DVI signal with 2CH audio to be converted to SDI in order to be shown on SDI displays. Furthermore, the device has a built-in default EDID and a recordable EDID that guarantee image display compatibility with source equipment.

## **PANELS**



#### **DIAGRAM**



## **FEATURES**

 Supports SDI output distance up to 60 meters (12G-SDI), 80 meters (6G-SDI) 100 meters (3G-SDI), 200 meters (HD-SDI), or 300 meters (SD-SDI)

#### Note:

- 1. Tested with Belden 1694A Cable. Operating distances may vary if used with cables of different specifications.
- This product does not process HDCP encrypted input signals. There will be no video output when the input signal contains content that is HDCP encrypted.
- Integrated audio embedded up to 8 CH PCM 48 kHz for HDMI or 2 CH (external L/R) for DVI audio
- Support SDI signal re-timing Cable Driver

## **SPECIFICATIONS**

Interfaces	
Input Port	1 HDMI (Type-A) 1 Unbalanced Stereo (3.5mm)
Output Port	2 12G-SDI(BNC) 1 HDMI(Type-A)
Video	
HDMI Compliance	HDMI 2.0 (DVI 1.0)

HDIVII Compliance	HDINI 2.0 (DVI 1.0)		
<b>HDCP Compliance</b>	Not Supported		
Input Signal Type	4K@60 8bit YUV 4:2:2		
Output Signal Type	4K@60 8bit YUV 4:2:2		
		Resolutions	
Maximum Input	HDMI	4096×2160p@60 (YUV 4:2:2)	
Maximum Output	HDMI	4096×2160p@60 (YUV 4:2:2)	
	SDI	4096×2160p@60 (YUV 4:2:2)	

	SDI	4096×2160p@60 (YUV 4:2:2)	
Audio			
Input Signal Types	HDMI, Unbalanced Stereo		
Output Signal Types	SDI		
Digital Formats	HDMI 2CH LPCM, 8CH LPCM		
Power			
Power Supply	5V/2.6A DC	(Locking)	
Power Consumption	6.138W (Ful	I Load)	
Enclosure			
Chassis Material	Metal (Steel	)	
Chassis Color	Black		
Dimensions (W×H×D)		mm×75mm [Case Only] mm×94mm [All Inclusive]	
Weight	347g		
Field Firmware Update			

# **ORDERING INFORMATION**

USB

Model No.	Product Description
PRO-H2SDI	HDMI to 12G-SDI Converter
PRO-SDI2H	12G-SDI to HDMI Converter
PRO-H2SDI-W	HDMI to 12G-SDI Converter
PRO-SDI2H-W	12G-SDI to HDMI Converter

