



**Soldering Gun 100W**  
**Model: D01848**

## IMPORTANT SAFETY INFORMATION

Please read these instructions carefully before use and retain for future reference

- When using electrical appliances basic safety precautions should always be followed.
- Check that the voltage indicated on the rating plate corresponds with that of the local network before connecting the appliance to the mains power supply.
- This appliance is not intended for use by persons (including children) with reduced physical, sensory or mental capabilities, or lack of experience and knowledge, unless they have been given supervision or instruction concerning use of the appliance by a person responsible for their safety.
- Children shall not play with the appliance. Cleaning and user maintenance shall not be made by children unless they are older than 8 and supervised.
- Do not operate the appliance with a damaged plug or cord, after a malfunction or after being dropped or damaged in any way.
- If the supply cord is damaged, it must be replaced by a qualified engineer in order to avoid injury or a hazard.
- Ensure there is sufficient space and ventilation around the appliance to allow the escape of heat and/or fumes.
- Do not expose to rain or moisture.
- Never place the product or part of it in water, or operate if your hands are wet.
- Soldering work must be conducted on a stable, non-combustible surface.
- Do not touch any metallic parts near the soldering tip.
- The iron must not be left unattended while it is connected to the supply mains.
- Turn the soldering iron off and unplug it when it is not in use.
- This device must be earthed through the mains lead and plug.

## OPERATION

**Note:** The first time you use the soldering iron, it may smoke slightly as the heating element dries out. This is normal and should only last for a few minutes.

- ONLY USE FOR ELECTRICAL WORK - Acidic solder will damage the iron tip.
- Connect the mains plug and turn on the power.
- When the trigger is pressed on the soldering gun the tip begins to heat up. Allow a few seconds for it to reach temperature then tin the tip with solder. The light will illuminate the work area.
- The maximum recommended time to keep the trigger ON is 12 seconds. Allow around 48 seconds between operations to allow the heating coils to cool.
- Keep the tip cleaned and tinned regularly during use.
- Clean off any dirt, rust or paint on the part you wish to solder.
- Heat the part with the soldering iron.
- Apply rosin-based solder to the part and melt it with the soldering iron.

**Note:** When using non-rosin-based solder, ensure you apply a soldering paste to the part before applying the solder.

- Wait for the solder to cool and harden before moving the soldered part.
- When the soldering work is done, switch off the power, clean the tip and tin with fresh solder to protect it from oxidation.
- Never file down the tips or attempt to clean using abrasives.

## SPECIFICATIONS

Voltage	220-240V AC 50Hz
Power	100W
Dimensions	200x160x50mm
Weight	560g

## TIP REPLACEMENT

- Replacing the tip should only be done when the iron is switched off and at room temperature.
- The tip can be changed or replaced by unscrewing the two nuts from the main tubes then pull out the tip.

**Caution:** Damage could occur if the iron is left on without the tip inserted.

- Replace the tip and tighten the two nuts with your fingers.
- Pliers should only be used to tighten the nut if loosening occurs when the iron is hot.
- Do not over tighten the nuts as the element could be damaged.

## CLEANING

- Cleaning should only be done when the iron is switched off and at room temperature.
- The iron may be cleaned with a damp cloth and a small amount of liquid detergent if necessary.
- Never submerge the soldering iron in liquid or allow any liquid to enter the case.
- Do not use any chemicals, abrasives or solvents that could damage the soldering iron.

## INFORMATION ON WASTE DISPOSAL FOR CONSUMERS OF ELECTRICAL & ELECTRONIC EQUIPMENT.

When this product has reached the end of its life it must be treated as Waste Electrical & Electronics Equipment (WEEE). Any WEEE marked products must not be mixed with general household waste, but kept separate for the treatment, recovery and recycling of the materials used. Contact your local authority for details of recycling schemes in your area.



Made in China

Faraday Drive, Preston, PR2 9PP (UK)  
Riverside One, Sir John Rogerson Quay, Dublin 2, D02 X576 (EU)